A comprehensive study of cryogenic cooled millimeter-wave frequency multipliers based on GaAs Schottky-barrier varactors

Johansen, Tom Keinicke; Rybalko, Oleksandr; Zhurbenko, Vitaliy; Bulcha, Berhanu; Hesler, Jeffrey

Published in:
International Journal of Microwave and Wireless Technologies

Link to article, DOI:
[10.1017/S1759078717001490](https://doi.org/10.1017/S1759078717001490)

Publication date:
2018

Document Version
Peer reviewed version

[Link back to DTU Orbit](#)

Citation (APA):
Johansen, T. K., Rybalko, O., Zhurbenko, V., Bulcha, B., & Hesler, J. (2018). A comprehensive study of cryogenic cooled millimeter-wave frequency multipliers based on GaAs Schottky-barrier varactors. *International Journal of Microwave and Wireless Technologies*, 1-10. <https://doi.org/10.1017/S1759078717001490>

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

RESEARCH PAPER

A Comprehensive Study of Cryogenic Cooled Millimeter-wave Frequency Multipliers Based on GaAs Schottky-Barrier Varactors

TOM K. JOHANSEN¹, OLEKSANDR RYBALKO¹, VITALIY ZHURBENKO¹, BERHANU BULCHA², AND JEFFREY HESLER³

The benefit of cryogenic cooling on the performance of millimeter-wave GaAs Schottky barrier varactor based frequency multipliers has been studied. For this purpose, a dedicated compact model of a GaAs Schottky barrier varactor using a triple anode diode stack has been developed for use with a commercial RF and microwave CAD tool. The model implements critical physical phenomena such as thermionic-field emission current transport at cryogenic temperatures, temperature dependent mobility, reverse breakdown, self-heating, and high-field velocity saturation effects. A parallel conduction model is employed in order to include the effect of barrier inhomogeneities which is known to cause deviation from the expected I-V characteristics at cryogenic temperatures. The developed model is shown to accurately fit the I-V-T dataset from 25 to 295 K measured on the varactor diode stack. Harmonic balance simulations using the model are used to predict the efficiency of a millimeter-wave balanced doubler from room to cryogenic temperatures. The estimation is verified experimentally using a 188 GHz balanced doubler cooled down to 77 K.

I. INTRODUCTION

Varactor frequency multipliers are often used as solid-state sources in the millimeter and submillimeter range. Frequency multipliers based on GaAs Schottky diode technology are commercially available up to several terahertz [1]. The use of these devices has been proved in different fields such as spectroscopy, satellite applications, communications, radio astronomy, etc. For several of these applications high efficiency and large fixed-tuned bandwidth are required. This in particular holds for dynamic nuclear polarization systems [2]. The polarization process relies on the power of electromagnetic radiation delivered to the sample. Traditionally, this power is delivered from sources using long wave-guiding structures, which loss and price scales with operating frequency. Alternatively, the multiplier can be placed close to the sample inside the polarization system, where the temperature of the environment is in the range from 77 to 100 K. Unfortunately, the power dissipation in the multiplier itself has been found to heat up the sample under test. Commercially available sources are typically not optimized for operation at cryogenic temperatures. Therefore, it may still be possible to improve the performance of the multipliers by design

optimization directly at cryogenic temperatures. This motivates the development of a dedicated compact model of GaAs Schottky barrier varactor diodes valid at cryogenic temperatures.

Compact diode models are available in most RF and microwave CAD software packages. Such diode models are generic, representing mainly the physical behavior of Silicon pn-junction diodes. Embedded with parasitic networks these diode models can be used to describe the performance of room temperature GaAs Schottky-based multipliers and mixers operating at frequencies up to several hundreds of GHz [3]. The temperature dependence of a Silicon pn-junction diode, however, is quite different from that of a GaAs Schottky barrier diode due to the different carrier transport mechanisms involved.

It is a well-established fact that the performance of Schottky-based millimeter-wave multipliers improves when cooled [4]. The main reason for the improvement is an increase of the bulk mobility in GaAs. The increase in bulk mobility translates directly into a decrease in series resistance of the Schottky barrier varactor and hence higher efficiency. For accurate prediction of multiplier performance at cryogenic temperature it is thus mandatory to include this temperature dependence of the bulk conductivity into the model formulation. The efficiency of Schottky-based multipliers is fundamentally limited by either forward conduction, including current saturation effects, or reverse breakdown mechanisms [5]. These effects must be properly accounted for in the compact model description. Also, at cryogenic temperatures barrier inhomogeneities

¹Department of Electrical Engineering, Technical University of Denmark, Kgs. Lyngby, Denmark

²NASA Goddard Space Flight Space Center

³Virginia Diodes Inc., Charlottesville, VA 22902, USA

influences the forward current conduction and must be accounted for as well.

In this paper, the performance of GaAs Schottky-based multipliers at cryogenic temperatures are studied. The paper expands on the authors previous study [6] on the efficiency at cryogenic temperatures for a 78 GHz frequency doubler reported in the literature [7]. The paper is structured as follows. In section II the static characterization in the temperature range from 5 - 295 K of a GaAs Schottky-barrier varactor using a triple anode diode stack mounted in a multiplier block is described. Section III describes the development of a dedicated compact model for the triple anode stack varactor. The Schottky-barrier varactor model is extended with a frequency dependent network to capture the effect of carrier inertia and displacement current in the epi-layer. Also, the skin effect in the substrate layer is modeled. This should make the developed compact model versatile enough to predict the performance of frequency multipliers even in the submillimeter wave frequency range. In section IV an experimental setup is presented which serves to verify the developed compact model against cryogenic measurements on a commercial 200 GHz frequency doubler from Virginia Diodes Inc. The conclusions are given in section V.

II. SCHOTTKY-BARRIER VARACTOR CHARACTERIZATION

A Schottky-barrier varactor diode mounted in a multiplier block was I-V tested for a range of temperatures from 5 - 295 K. The diode, which consists of three anodes in series, has a total zero-bias capacitance of 26 fF. A two stage closed cycled cryogenic system is used to set the varactor multiplier at different temperatures. By applying Apizon N thermal grease between the varactor multiplier block and the second stage cryogenic system, effective thermal coupling was achieved. Furthermore, a temperature sensor from Lake Shore was mounted on the varactor multiplier block to monitor the temperature precisely. A sweepable Keithley source unit was used to measure the I-V performance. The measured I-V characteristics in the interval from 5 K to 295 K are shown in Fig. 1. The measured forward I-V-T dataset were compared to the standard diode equation

$$I = I_s \left[\exp \left(\frac{q(V - IR_s)}{\eta kT} \right) - 1 \right] \quad (1)$$

where η is the ideality factor, R_s is the series resistance, I_s is the saturation current, q is the electron charge, and k is Boltzmann constant. The standard diode I-V equation in (1) should provide a good description of a Schottky-barrier diode with a forward transport current dominated by thermionic-emission [8], [9]. In this case the saturation current can be described by

$$I_s = AA^{**}T^2 \exp \left(\frac{-q\Phi_b}{kT} \right) \quad (2)$$

Fig. 1. Forward I-V-T characteristics.

where A is the diode area, A^{**} is the modified Richardson constant, and Φ_b is the barrier height. The I-V measurements in Fig. 1, however, shows that when the multiplier is cooled below roughly 155 K, abnormal current transport mechanisms other than thermionic-emission becomes important.

To investigate the current transport at cryogenic temperatures in more details, Fig. 2 shows the ideality factor

$$\eta = \frac{q}{kT} \left(\frac{dV}{d \ln I} \right) \quad (3)$$

extracted from the slope of the I-V characteristics at different temperatures. It is found that the ideality factor increases with decreasing temperatures. For a constant current level of $1E-6$ A the ideality factor changes from a value of ~ 3.2 at 295 K to ~ 20.3 at 25 K. The increase

Fig. 2. Extracted ideality factor dependence on temperature in the range 25-295 K for a constant current of $1E-6$ A.

in ideality factor with decreasing temperature may be explained in part by a tunneling component as described by the thermionic-field-emission and field-emission transport

theory of Padovani and Stratton [10]. It may also be a consequence of inhomogeneities at the metal-semiconductor interface [11]. A possible physical explanation for the electron transport in the presence of such interfacial inhomogeneities has been proposed by Tung [12]. According to Tung's model, current transport across the Schottky barrier is affected by parasitic patches with lower barrier heights than the background. The effect of the parasitic patches will be hardly noticeable at room temperature but manifest themselves at lower temperatures [13]. The Richardson's plot is shown in Fig. 3. According to (2) a

Fig. 3. Richardson's plot in the temperature range of 25-295 K for a constant current of $1E - 6$ A.

plot of $\ln(I_s/T^2)$ versus $(kT)^{-1}$ should yield a straight line with slope of $-\Phi_b$ and intersect of $\ln(AA^{**})$. From Fig. 3 it is clearly seen that the extracted saturation currents do not follow the expected linear trend in the Richardson's plot. This is a further confirmation that the current transport can not be described by thermionic emission and may be affected by parasitic patches with a lower barrier heights than the background. Therefore, for improved accuracy at cryogenic temperatures our compact modeling approach implements a parallel conduction model description to account for the effect of parasitic patches on the forward I-V characteristics.

III. SCHOTTKY-BARRIER VARACTOR MODELING

The standard quasi-static lumped-element model of a Schottky diode, consisting of the parallel dynamic junction conductance and capacitance followed by a fixed series resistance, is known to be of limited validity at millimeter- and submillimeter waves [14]. For this frequency range the Schottky diode model must be extended to take into account of the charge carrier inertia and displacement current in the undepleted part of the device. The frequency dependence of the spreading resistance in the n^+ -doped GaAs substrate due to the skin effect must also be taken

into account [15]. At the plasma frequency, where the inductive effect associated with the charge carrier inertia resonate with the capacitive effect associated with the displacement current, the losses in the device increase sharply. At millimeter- and submillimeter-waves the charge carrier inertia and displacement current in the substrate can be neglected [16]. For the low to moderately doped GaAs epilayer, however, the carrier inertia and displacement current can have a strong effect on the performance at submillimeter-waves [16], [17]. The extended model for a homogeneous Schottky-barrier varactor is shown in Fig. 4a). The parallel conduction model in Fig. 4b) is proposed here to account for the inhomogeneities associated with the Schottky-barrier varactor diode stack. The models shown in

Fig. 4. a) Extended homogeneous Schottky-barrier varactor model valid far below the plasma frequency of the substrate. b) Parallel conduction model for inhomogeneous Schottky-barriers.

Fig. 4a) and Fig. 4b) are implemented as Symbolic Defined Devices (SDDs) in Keysight ADS. For a consistent SDD implementation the capacitive elements must be defined in terms of voltage dependent charge functions. The inductive elements must be defined in term of current dependent fluxes. As the flux is dependent on the current flowing through the inductive element it must be defined using an implicit expression in our SDD implementation.

A) Forward I-V-T Characteristics

From the characterization of the Schottky barrier varactor in the previous section it was found that the thermionic-emission theory alone cannot describe the current transport taking place in the Schottky barrier varactor. From the increase in ideality factor with decreasing temperature it is plausible that tunneling through the barrier contributes to the current transport [8]. The expected importance of the tunneling current at a given temperature can be assessed by comparing the thermal energy, kT , to the characteristic energy for tunneling, E_{00} . At low temperatures where $kT \ll E_{00}$, tunneling through the barrier at an energy-level corresponding to the Fermi-level is the dominating transport mechanism. This current transport mechanism is called field-emission. In the temperature range where $kT \approx E_{00}$, thermionic-field-emission dominates where thermally

excited carriers tunnels through a narrower barrier than at field-emission. Thermionic-emission is expected to be the dominating current transport mechanism only for higher temperatures where $kT \gg E_{00}$. Analytical expressions for the current transport by field-emission and thermionic-field-emission have been derived by Padovani and Stratton [10]. These expressions, however, are generally too complicated to form the basis for a compact modeling formulation. Instead, a current transport model which combines the main features of the field-emission, thermionic-field-emission, and thermionic-emission transport mechanisms has been proposed [4]. This transport model modifies the forward transport current into

$$I_j = AA^{**}\Theta(T)^2 \exp\left(\frac{-q\Phi_b}{k\Theta(T)}\right) \left[\exp\left(\frac{qV_j}{k\Theta(T)}\right) - 1 \right] \quad (4)$$

where the so-called slope-parameter $\Theta(T) = \eta T$ has been introduced. The temperature dependence of the slope-parameter is given as

$$\Theta(T) = \Theta_f \coth\left(\frac{\Theta_f}{T}\right) \quad (5)$$

with

$$\Theta_f \approx \alpha \frac{q\hbar}{k} \sqrt{\frac{N_d}{4\epsilon_s m^*}} \quad (6)$$

where $\hbar$ is the reduced Planck's constant, N_d is the doping of the epi-layer, ϵ_s is the semiconductor permittivity, and m^* is the effective mass of electrons in the conduction band. From above it is observed that the temperature dependence of the I-V characteristic for a given metal-semiconductor contact are determined alone by two unknown parameters; the barrier height and the doping of the epilayer. A scaling factor, α , is introduced in our modeling approach for added flexibility. Equation (4) has the property of reducing to the field-emission equation of Padovani and Stratton in the limit of $T \rightarrow 0$ K. In the high temperature limit, $\Theta(T) \rightarrow T$, and (4) becomes identical to the ideal thermionic-emission expression corresponding to (1). It is interesting to investigate the validity of (4) for the Schottky barrier varactor triple-anode diode stack considered in the previous section. To this end, the slope parameter at each temperature is extracted from the I-V characteristic at a constant low current level of $1E-6$ A. Fig. 5 shows the extracted slope-parameters compared to a calculated model response using (5) and (6) with $\alpha = 1.59$, $N_d = 2E17 \text{ cm}^{-3}$, $\epsilon_s = 12.9\epsilon_0$, and $m^* = 0.068m_0$. To model the effect of a *triple-anode* diode stack a leading multiplication factor of 3 is included in the calculation of the slope parameter. The slope-parameter can be seen as an effective temperature of the Schottky barrier varactor. Therefore, a plot proportional to $3T$ is also included as a reference in Fig. 5. In the high temperature range this plot approaches the extracted slope-parameter and thermionic-emission will dominate the current transport. For a compact model implementation the I-V characteristic in (4) can be formulated in terms of an temperature dependent saturation

Fig. 5. Extracted slope parameter versus temperature for a constant current of $1E-6$ A. The dashed line shows the calculated model response using (5) and (6) with $\epsilon_s = 12.9\epsilon_0$, $N_d = 2E17 \text{ cm}^{-3}$, $m^* = 0.068m_0$, and $\alpha = 1.59$.

current $I_s(T)$ and temperature dependent ideality factor $\eta(T)$ as

$$I_j = I_s(T) \left(\exp\left(\frac{qV_j}{\eta(T)kT}\right) - 1 \right) \quad (7)$$

similar to the standard diode equation in (1). The temperature dependence of the saturation current, however, is evaluated as

$$I_s(T) = I_s(T_{nom}) \left(\frac{\Theta(T)}{\Theta(T_{nom})} \right)^2 \times \exp\left(\frac{q\Phi_b}{k} \left(\frac{1}{\Theta(T_{nom})} - \frac{1}{\Theta(T)} \right)\right) \quad (8)$$

where $I_s(T_{nom})$ represents the saturation current extracted at the model reference temperature T_{nom} . Similarly, the temperature dependent ideality factor is evaluated as

$$\eta(T) = \eta(T_{nom}) \frac{\Theta(T)}{T} \frac{T_{nom}}{\Theta(T_{nom})} \quad (9)$$

where $\eta(T_{nom})$ is the ideality factor extracted at T_{nom} .

The expression for the forward I-V characteristic in (7) remains valid for the *triple-anode* varactor diode stack only up to the so-called flat-band condition [18]. The flat-band condition is given as $V_{fb} = V_{bi} - V_j = 3 \times kT/q$ where the built-in potential has been introduced. The built-in potential is determined in terms of the barrier height and epi-layer doping as

$$V_{bi} = \Phi_b - 3 \times \frac{kT}{q} \ln\left(\frac{N_c}{N_d}\right) \quad (10)$$

with N_c representing the effective density of states in the conduction band for GaAs. At voltages above flat-band the device will act like a resistor. To model this resistive behavior a linear extrapolation of the I-V characteristic in (4)

above flatband is proposed

$$I_j = I_s(T) \left(\exp \left(\frac{qV_{fb}}{\eta(T)kT} \right) \left(1 + \frac{q(V_j - V_{fb})}{\eta(T)kT} \right) - 1 \right) \quad (11)$$

Conduction above flat-band becomes important to accurately model the current flow at cryogenic temperatures in the presence of barrier inhomogeneities as discussed next.

Modeling barrier inhomogeneities

It was shown in section 2 that the Richardson's plot could not be described in terms of the thermionic emission theory using a single constant barrier height. With the increased insight following from the discussion in section 3.1 it can be seen that one should actually plot $\ln(I_s/\Theta(T)^2)$ versus $(k\Theta(T))^{-1}$ to extract the barrier height Φ_b from the slope. It is found, however, that the slope is not constant over temperature even with this improved extraction technique. As shown in Fig. 6 the extracted *effective* barrier height for a *single anode* shows a nearly linearly decreasing trend with the inverse of the effective temperature $\Theta(T)$. Such

Fig. 6. Extracted effective barrier height plotted versus $1000/\Theta(T)$ for a constant current of $1E-6$ A. The dashed line shows the calculated model response using (12) with $\Phi_b^0 = 1.16$ eV and $\sigma_s^2 = 0.075$ eV².

an observation can be explained by the presence of barrier inhomogeneities. Werner and Güttler [19] have shown that a spatial fluctuating Schottky contact with Gaussian barrier distribution can be described as

$$\Phi_b = \Phi_b^0 - \frac{\sigma_s^2}{2k\Theta(T)} \quad (12)$$

where Φ_b^0 is the mean barrier height and σ_s is the standard deviation. In (12) we have substituted the temperature as given in [19] with the slope parameter $\Theta(T)$ to account for field-emission and thermionic-field-emission. As shown in Fig. 6 the extracted effective barrier height can be reasonably well represented by (12). It should be mentioned that a refined model of barrier inhomogeneities has been proposed by Tung [12] where a bias voltage dependence is included for the effective barrier height. Based on the

experimental available data for the triple-anode varactor stack there seems to be little evidence that the voltage dependence is significant. The effect of barrier inhomogeneities on the forward I-V-T characteristics is subtle. For a homogeneous Schottky contact it is well known that the bias voltage necessary to reach a given current level increases at lower temperatures due to the temperature dependence of the slope parameter. In the presence of barrier inhomogeneities, regions of the Schottky contact will have a lower barrier than expected for the given metal-semiconductor material system. As a consequence, the flatband condition is reached earlier for the regions with low barrier heights than for the higher barrier regions. Once the flatband condition is reached, the low barrier regions stops to contribute significantly to the overall current conduction and the higher barrier regions begins to dominate. It is not sufficient to implement the effective barrier height as given in (12) into our compact model formulation as the current conduction caused by regions with different barrier heights can not be predicted in this way. Instead a parallel conductance model must be applied. As was shown by Ohdomari and Tu [20] the effective barrier height of a parallel conductance model consisting of a high barrier region of area A_{hb} and a low barrier region of area A_{lb} can be represented as

$$\Phi_b = -\frac{k\Theta(T)}{q} \ln \left(X_j \exp \left(\frac{-q\Phi_{hb}}{k\Theta(T)} \right) + (1 - X_j) \exp \left(\frac{-q\Phi_{lb}}{k\Theta(T)} \right) \right) \quad (13)$$

where Φ_{hb} and Φ_{lb} is the barrier height associated with the high and low barrier region, respectively, and $X_j = A_{hb}/(A_{hb} + A_{lb})$ is the fraction of the total Schottky contact area allocated to the high barrier region. A similar modeling approach is followed here. For added flexibility, however, the slope factors for both contacts are allowed to be different in our modeling approach. This is implemented through different fitting factors, α_{hb} and α_{lb} , for the high and low barriers, respectively. Fig. 7 shows the parallel conduction modeling compared to the measured forward I-V-T characteristics discussed in section 2. For clear illustration I-V characteristics for a temperature increment of 30 K is shown. In general, the parallel conduction model is able to accurately reproduce the measured I-V-T characteristics the full range of temperatures from 25 K to 295 K. The parallel conduction model requires a total of 8 parameters. Their values corresponding to a triple anode varactor stack are given in the caption of Fig. 7. The effect of barrier inhomogeneities can be deactivated from the model by setting the area distribution factor to $X_j = 1.0$. It is interesting to notice that even though only 2 % of the total area is allocated to the low barrier region it has a strong effect on the modeled I-V characteristics at cryogenic temperatures. The modeling at the lowest temperatures of 25 K and 55 K can be improved by implementing more junctions in parallel. As the main interest for the present work is to demonstrate

Fig. 7. Measured (symbols) and modeled (dashed lines) forward I-V-T characteristics. The model is based on the parameters: $I_s = 1.475E - 13$ A, $\eta = 3.2$, $\Phi_{hb} = 2.96$ eV, $N_d = 2E17$ cm⁻³, $\alpha_{hb} = 1.59$, $X_j = 0.98$, $\phi_{lb} = 2.12$, eV, $\alpha_{lb} = 0.71$.

improved modeling of multiplier performance down to 77 K the extra model complexity is not worthwhile.

B) C-V characteristic

The junction capacitance of the Schottky barrier triple-anode stacked varactor diode is modeled as

$$C_j = \frac{C_{jo}}{\sqrt{1 - \frac{V_j}{V_{bi} - 3\frac{kT}{q}}}} + C_{corr} \quad (14)$$

where C_{jo} is the zero-biased junction capacitance and C_{corr} is a first order correction term for edge effects in very small submillimeter-wave diodes. The singularity at high forward bias in (14) is avoided by a linear extrapolation of the junction capacitance above the voltage $F_c V_j$ where F_c is a factor between 0 and 1.

C) Series impedance

The series impedance of the Schottky varactor stack contains three contributions; the impedance, $Z_{epi}(j\omega)$, due to the undepleted part of the epi-layer, the spreading resistance, R_{sub} , of the heavily doped substrate layer including the frequency dependent skin-effect impedance $Z_{skin}(j\omega)$, and the contact resistance. The contact resistance is absorbed into the substrate resistance in our modeling approach. Furthermore, it is assumed that only the resistive part of the epi-layer impedance varies with temperature. The temperature dependence is mainly due to the bulk mobility, $\mu_n(T)$, of moderate doped n-type GaAs. The low-frequency series resistance of the Schottky varactor stack can be partitioned into two parts using the parameter X_r according to

$$R_s(T) = X_r R_s(T_{nom}) \left(\frac{T}{T_{nom}} \right)^{0.89} + (1 - X_r) R_s(T_{nom}) \quad (15)$$

where the exponent of 0.89 is proposed to account for the expected temperature dependence of the bulk mobility for GaAs [21]. The first and second terms in (15) describes the parts of the low-frequency series resistance allocated to the epi-layer and substrate, respectively. For an accurate prediction of multiplier efficiency it is necessary to include the velocity saturation of the mobile carriers in the undepleted part of the epi-layer which occurs at high current levels [22]. This is implemented in the SDD model using an empirical current dependent function

$$R_{epi}(T, i(t)) = R_{epi0}(T, i(t) \approx 0) \left(1 + \left(\frac{i(t)}{i_{sat}(T)} \right)^6 \right) \quad (16)$$

where $R_{epi0}(T, i(t) \approx 0)$ is the epi-layer resistance before the onset of current saturation, $i(t)$ is the current flowing through the epi-layer and $i_{sat}(T)$ is a characteristic current for the onset of velocity saturation effects. This approach is similar to that of Kollberg et al. [22]. The temperature dependence of the characteristic current is implemented as

$$i_{sat}(T) = i_{sat}(T_{nom}) \left(\frac{T}{T_{nom}} \right)^{-0.37} \quad (17)$$

which corresponds to an expected increase of 65 % for the saturated velocity of GaAs at 77 K [4]. The displacement current in the epi-layer is modeled as a linear temperature independent capacitance

$$C_{epi} = \frac{1}{R_{epi}(T_{nom})\omega_d} \quad (18)$$

where $\omega_d = qN_d\mu_n(T_{nom})/\epsilon_s$ is the dielectric relaxation frequency [16]. As the temperature dependence of the epi-layer resistance and the dielectric relaxation frequency both depends on the bulk mobility but in an opposite manner it is justified to assume a temperature independent epi-layer capacitance. The carrier inertia is modeled as a linear temperature independent inductance

$$L_{epi} = R_{epi}(T_{nom})/\omega_s \quad (19)$$

where $\omega_s = q/m^*\mu_n(T_{nom})$ is the scattering frequency [16]. Again it is well justified to assume temperature independence for the epi-layer inductance.

The impedance of the substrate layer must include the increase with frequency due to the skin effect. In our modeling approach the frequency dependence of the impedance of the substrate layer is implemented as

$$Z_{sub}(j\omega) = R_{sub} + Z_{skin}(j\omega) = R_{sub} \left(1 + \frac{R_{skin}(j\omega_{skin})}{R_{sub}} \sqrt{\left(\frac{2j\omega}{\omega_{skin}} \right)} \right) \quad (20)$$

in terms of the skin effect resistance $R_{skin}(j\omega_{skin})$ at frequency ω_{skin} . The frequency dependent substrate impedance is implemented in the SDD by applying a frequency dependent weighting function to the low frequency resistive part of the substrate impedance, R_{sub} .

D) Reverse breakdown

The reverse breakdown is the limiting mechanisms for the Schottky barrier varactor at high reverse voltages. The reverse breakdown is modeled using the standard ADS implementation. The empirical formulation leads to an exponentially increase in current conduction for reverse voltages exceeding the breakdown voltage

$$I_{br} = -I_{bv} \exp\left(-\frac{q(V_j + BV)}{kTN_{bv}}\right) + I_{bv} \exp\left(-\frac{qBV}{kTN_{bv}}\right) \quad (21)$$

where BV is the breakdown voltage, I_{bv} the breakdown saturation current, and N_{bv} the breakdown ideality factor.

E) Self-heating

A first-order thermal network, similar to the one described in [6], is included into our model formulation to simulate self-heating effects.

IV. EFFICIENCY OF MILLIMETER-WAVE FREQUENCY MULTIPLIERS AT CRYOGENIC TEMPERATURES

A) Cryogenic setup

A commercially available D200 frequency doubler from VDI has been used to experimentally study the performance at cryogenic temperatures and to validate the diode model. The D200 frequency doubler was optimized for 188 GHz output frequency operation by controlling the bias voltage. The input signal was generated by a narrow band microwave source providing 207 mW of power at 94 GHz. The generated power level was verified by a VDI Erickson power meter PM5. The experimental setup is shown in Fig. 8. To reach the doubler temperature of 77 K the Dewar flask (1) is filled with liquid nitrogen. The doubler is placed directly into the Styrofoam container (2) minimizing the thermal losses and providing thermal isolation while maximizing cooling efficiency. To control the temperature the calibrated temperature meter Omega HH804U (3) was used. A platinum resistance temperature detector (RTD) head is placed directly on the surface of the doubler block to maximize the temperature measurement accuracy. The Schottky junction temperature is expected to be somewhat higher due to power dissipation in the device.

To be able to control the temperature of the multiplier, helium gas is applied from the balloon through a pipe directly to the input valve of the Dewar flask. Helium gas flow can change the cooled evaporation rate of the liquid nitrogen from the output valve. In this way, the temperature inside the Styrofoam container can be adjusted. The performance of the doubler was measured with 10 K step at temperatures from 77 K to 300 K. The output signal was recorded by an Agilent Spectrum Analyzer with OML mixers.

Fig. 8. Photograph of the experimental setup, complete view.

B) Millimeter-wave balanced doubler design

The frequency doubler is based on a varactors diode chip with a total of 6 anodes in a anti-series balanced configuration [7]. The principle schematic of the frequency doubler as used for the harmonic balance simulation is shown in Fig. 9. The advantage of the anti-series balanced config-

Fig. 9. Principle schematic of the circuit setup for harmonic balance simulation of frequency doublers in an anti-series configuration of diode arrays.

uration is suppression of odd-order harmonics, while the amplitude of the second harmonic is double as high as for the case of an unbalanced single diode doubler. Three diodes are connected in series in each branch in order to enhance the power handling capability. The arrangement of three series diodes is equivalent to a single Schottky diode with three times the reverse breakdown voltage. In simulations each triple diode series stack is represented with the compact model developed in the previous section. In the

anti-series configuration, diode arrays are fed out-of-phase by an input signal source through a balancing transformer T_1 . Turns ratio of the transformer is equal to 1. The diodes are reverse biased with negative V_d , which is chosen to maximize efficiency at a given input power. DC blocking capacitors C_{cl} are placed at the output of the transformer to prevent DC current flowing into the transformer. DC feeding inductors L_{cl} are used to isolate the RF signal from DC voltage source and provide DC ground. The generator and load impedances (Z_g and Z_L respectively) are frequency dependent and chosen to maximize doubler efficiency. Z_g is conjugate matched to the input impedance of the doubler at the frequency of the input signal and represents a short circuit at the 2nd harmonic. The load impedance Z_L , on the other hand, is conjugate matched at the 2nd harmonic of the input signal, and represents a short circuit at the frequency of the input signal. In this analysis, the losses in the matching circuits are neglected. In order to compare the efficiency as calculated by circuit simulation using the schematic in Fig. 9 to the measured flange-to-flange efficiency it is necessary to account for the input and output coupling losses. As proposed in [14] the measured and simulated flange-to-flange efficiency, η_{meas} and η_{sim} , respectively, can be related as

$$\eta_{meas} = \alpha\beta\eta_{sim} \quad (22)$$

where $\beta \sim 0.875$ is the assumed coupling factor of the output power and $\alpha \sim 0.8$ is the assumed coupling factor of the input power. The coupling factor of $\alpha \sim 0.8$ for the input power seems reasonable given the rather long waveguide leading from the 94 GHz source to the multiplier located inside the Dewar flask.

C) Varactor model verification

The harmonic-balance analysis is applied to the circuit in Fig. 9 to theoretically estimate doubler efficiency at a fixed input power of about 207 mW and frequency of interest 188 GHz. Initially values for the zero bias capacitance, breakdown voltage, series resistance, and embedded impedances are taken from [23] for a similar 200 GHz frequency doubler. These parameters are given in Table 1 together with the optimized parameters taking into account the measured zero bias capacitance of 26 fF and breakdown voltage of 26 V for the triple anode stack varactors in the present D200 frequency doubler. The series resistance, R_s , and zero bias capacitance, C_{jo} , model parameters controls the efficiency at room temperature together with the embedded impedances and the bias voltage. The partitioning factor, X_r , for the series resistance controls the improvement of the efficiency with reduced temperature and is initially set to 0.6. The graph in Fig. 10 shows esti-

mated and measured efficiency versus temperature using the initial parameters and the optimized parameters for the present doubler. The measured efficiency of the doubler improves from $\sim 21\%$ at 300 K to $\sim 31.5\%$ at 77 K and confirms the expected improvement with cooling. The sim-

Fig. 10. Efficiency versus temperature. Solid line with crosses represents measured efficiency. Dashed line represents initial simulated efficiency using $C_{jo} = 18.7$ fF and $V_{BV} = 28.5$ V while solid line represents the optimized simulated efficiency using $C_{jo} = 26$ fF and $V_{BV} = 26$ V.

ulated efficiency using the initial parameters overestimates the measured efficiency of the doubler whereas the optimized parameters shows good agreement. The deviation observed around the temperature range from 150 to 200 K is believed to be mainly due to measurement inaccuracy. For the optimized case the series resistance remains at a value of 12.0Ω for a best estimate of the measured efficiency at room temperature. The partitioning factor is lowered to 0.47 to capture the slope of the efficiency versus temperature curve. The complete list of model parameters for the Schottky-barrier varactor using the triple anode diode stack is summarized in Table 2. Not all model param-

Table 2. Model parameters for Schottky-barrier varactor.

I_s [A]	1.48E-13	N	3.2	R_s [Ω]	12.0
X_r	0.47	I_{sat} [A]	0.247	μ_n [$cm^2/V \cdot s$]	4600
R_{skin} [Ω]	0.1	f_{skin} [GHz]	188	C_{jo} [fF]	26.0
M_j	0.5	F_c	0.9	C_{corr} [fF]	0.0
BV [V]	26	I_{bv} [A]	50E-6	N_{bv}	1.0
Φ_{hb} [eV]	2.96	N_d [cm^{-3}]	2E17	α_{hb}	1.59
X_j	0.98	Φ_{lb} [eV]	2.12	α_{lb}	0.71

Table 1. Initial and optimized parameters.

	C_{jo} [fF]	R_s [Ω]	X_r	BV [V]	Z_g [Ω]	Z_L [Ω]
Init. param.	18.7	12.0	0.6	28.5	12+j78	19.5+j39
Opt. param.	26.0	12.0	0.47	26.0	7.9+j57	16.4+j31

eters are of equal importance for the prediction of the measured efficiency of the 200 GHz doubler. In particular, parameters describing current saturation, carrier inertia and displacement current in the epi-layer, and the skin effect in the substrate layer are superfluous for the considered 200 GHz doubler. These effects, however, will become limiting factors for frequency multipliers at higher frequencies and should be included for a versatile compact model formulation. The barrier inhomogeneities was seen to have a significant effect on the forward I-V curves at cryogenic

temperatures. It is interesting to investigate the influence of barrier inhomogeneities on the efficiency of the 200 GHz doubler. The effect is expected to be strongest at lowest temperatures. Therefore Fig. 11 shows the simulated efficiency at 77 K for a high-barrier area to total barrier area ratio ranging from 0.8 to 1.0. It is observed that the influ-

Fig. 11. Simulated efficiency versus high-barrier to total barrier area at $T=77$ K.

ence on the simulated efficiency going from $X_j=0.98$ to $X_j=1.0$ is negligible. A possible explanation for this is that the input source drive level at 94 GHz is not sufficient to drive the varactor deep into its forward conduction region. Also, the signal swing across each diode stack remains negative for most part of the cycle. Multipliers which experience larger degree of forward conductance are expected to show greater dependence on barrier inhomogeneities.

V. CONCLUSION

In this work the benefit of cryogenic cooling for millimeter-wave frequency doublers based on GaAs Schottky-barrier varactors has been studied. For this purpose a triple-anode diode stack mounted in a multiplier block has been characterized in the temperature range from 5 to 295 K. The measurements of the varactor's I-V-T characteristics reveal abnormal current transport other than thermionic emission. It was shown that the abnormal current transport can be explained in part by thermionic-field-emission and field-emission current transport and in part by barrier inhomogeneities. A dedicated compact model of the GaAs Schottky barrier varactor taking these effects into account was described. It has been verified experimentally that the efficiency of a commercially available 188 GHz doubler improves up to 31.5 % when cooled to 77 K. The main reason for the increasing efficiency with cooling is the drop in series resistance which is well predicted by the developed compact model.

REFERENCES

- [1] T. W. Crowe, W. L. Bishop, D. W. Porterfield, J. L. Hesler and R. M. Weikle: Opening the Terahertz Window With Integrated Diode Circuits. *IEEE J. Solid-State Circuits*, **40** (2005), 2104-2110.
- [2] J. H. Ardenkjær-Larsen, B. Fridlund, A. Gram, G. Hansson, L. Hansson, M. H. Lerche, R. Servin, M. Thanning and K. Golman: Increase in signal-to-noise ratio of >10,000 times in liquid-state NMR. *Proceedings of National Academy of Sciences*, **40** (2003), 10158-10163.
- [3] L. Yan: Design of integrated circuits approaching terahertz frequencies. PhD thesis, Technical University of Denmark, 2013.
- [4] J. T. Louhi, A. V. Raisanen, and N. R. Erickson: Cooled schottky varactor frequency multipliers at submillimeter wavelengths. *IEEE Trans. Microwave Theory and Techniques*, **41** (1993), 565-571.
- [5] J. East and I. Mehdi: Temperature Effects in Varactors and Multipliers, 12th International Symposium on Space Terahertz Technology, 2001.
- [6] T. K. Johansen, O. Rybalko, V. Zhurbenko, S. Bowen, J. Hesler and J. H. Ardenkjær-Larsen: Modeling of Schottky Barrier Diode Millimeter-Wave Multipliers at Cryogenic Temperatures, *Proc. SBMO/IEEE MTT-S International Microwave and Optoelectronics Conference (IMOC)*, Porto de Galinhas, Brazil, 2015.
- [7] D. W. Porterfield, T. W. Crowe, R. F. Bradley and N. R. Erickson: A high-power fixed-tuned millimeter-wave balanced frequency doubler, *IEEE Trans. Microwave Theory and Techniques*, **47** (1999), 419-425.
- [8] S. M. Sze and K. K. Ng: *Physics of Semiconductor Devices*, 3rd Edition, Wiley-Interscience, 2007.
- [9] R. F. Pierret: *Semiconductor Device Fundamentals*, Addison Wesley, 1996.
- [10] F. A. Padovani and R. Stratton: Field and Thermionic-Field Emission in Schottky Barriers, *Solid-State Electronics*, **9** (1966), 695-707.
- [11] P. M. Gammon, A. P. Tomas, V. A. Shah, O. Vavasour, E. Donchev, J. S. Pang, M. Myronov, C. A. Fisher, M. R. Jennings, D. R. Leadley and P. A. Mawby: Modelling the inhomogeneous SiC schottky interface, *Journal of Applied Physics*, **114** (2013).
- [12] R. T. Tung: Electron Transport of Inhomogeneous schottky barriers, *Applied Physics Letters*, **58** (1991), 2821-2823.
- [13] D. Korucu, A. Turut and H. Efeoglu: Temperature dependent I-V characteristics of an Au/n-GaAs schottky diode analysed usings Tung's model, *Physica*, **414** (2013), 35-41.
- [14] D. Pardo, J. Grajal, C. G. Perez-Moreno and S. Perez: An assessment of available models for the design of schottky-based multipliers up to THz frequencies, *IEEE Trans. Terahertz Science and Techn.*, **4** (2014), 277-287.
- [15] Spreading resistance as a function of frequency, *IEEE Trans. Microwave Theory and Techniques*, **MTT-15** (1967), 101-109.
- [16] T. W. Crowe: GaAs schottky barrier mixer diodes for the frequency range 1-10 THz, *Int. J. Infrared Millimeter Waves*, **10** (1989), 765-777.
- [17] W. M. Kelly and G. T. Wrixon: Conversion losses in schottky-barrier diode mixers in the submillimeter region, *IEEE Trans. Microwave Theory and Techn.*, **MTT-27** (1979), 665-672.
- [18] E. L. Kollberg, H. Zirath and A. Jelenski: Temperature-variable characteristics and noise in metal-semiconductor junctions, *IEEE Trans. Microwave Theory and Techn.*, **MTT-34** (1986), 913-922.
- [19] J. H. Werner and H. H. Güttler: Barrier inhomogeneities at schottky contacts, *Journal of Applied Physics*, (1991), 1522-1533.

- [20] I. Ohdomari and K. N. Tu: Parallel silicide contacts, *Journal of Applied Physics*, **51** (1980), 3735-3739.
- [21] A.-Y. Tang, E. Schlecht, R. Lin, G. Chattopadhyay, C. Lee, J. Gill, I. Mehdi, and J. Stake: Electro-thermal model for multi-anode schottky diode multipliers, *IEEE Trans. THz Sci. Technol.*, **2** (2012), 290-298.
- [22] E. L. Kollberg, T. J. Tolmunen, M. A. Frerking, and J. R. East: Current saturation in submillimeter wave varactors, *IEEE Trans. Microwave Theory and Techn.*, **40** (1992), 831-838.
- [23] D. Porterfield: A 200 GHz Broadband, Fixed-Tuned, Planar Doubler, 12th International Symposium on Space Terahertz Technology, 1999.