640 Gbit/s optical time-division add-drop multiplexing in a non-linear optical loop mirror

Mulvad, Hans Christian Hansen; Galili, Michael; Oxenløwe, Leif Katsuo; Clausen, Anders; Grüner-Nielsen, Lars Erik; Jeppesen, Palle

Published in:
IEEE/LEOS Winter Topicals Meeting Series

Link to article, DOI:
[10.1109/LEOSWT.2009.4771731](https://doi.org/10.1109/LEOSWT.2009.4771731)

Publication date:
2009

Document Version
Publisher's PDF, also known as Version of record

[Link back to DTU Orbit](#)

Citation (APA):
Mulvad, H. C. H., Galili, M., Oxenløwe, L. K., Clausen, A., Grüner-Nielsen, L. E., & Jeppesen, P. (2009). 640 Gbit/s optical time-division add-drop multiplexing in a non-linear optical loop mirror. In *IEEE/LEOS Winter Topicals Meeting Series* (pp. 209-210). IEEE. <https://doi.org/10.1109/LEOSWT.2009.4771731>

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

640 Gbit/s Optical Time-Division Add-Drop Multiplexing in a Non-Linear Optical Loop Mirror

H. C. Hansen Mulvad, M. Galili, L. K. Oxenløwe, A. T. Clausen and P. Jeppesen
DTU Fotonik, Technical University of Denmark
Ørstedes Plads 343, DK-2800 Kgs. Lyngby, Denmark
Email: hchm@fotonik.dtu.dk

L. Grüner-Nielsen
OFS Fitel Denmark ApS
Priorparken 680
DK-2605 Brøndby, Denmark

Abstract—Error-free 640 Gbit/s all-optical time-division add-drop multiplexing is demonstrated using a non-linear optical loop mirror. Both the add- and drop operations are achieved simultaneously by switching.

I. INTRODUCTION

Time-division add-drop multiplexing (TADM) consists in extracting and replacing the individual data pulses in a serial data signal. This is an important networking functionality in the context of optical time-division multiplexed (OTDM) systems. OTDM data signals are formed by bit-interleaving narrow-pulsed, identical-wavelength data channels at a low base rate (e.g. 10 Gbit/s), enabling aggregate bit rates currently up to 640 Gbit/s. Fibre-based switches are very promising candidates for TADM up to 640 Gbit/s, since they are based on the non-linear Kerr effect which has an ultra-fast femtosecond response. Earlier, error-free fibre-based TADM has been demonstrated at 160 Gbit/s using a Kerr shutter [1] and a non-linear optical loop mirror (NOLM) [2], and recently at 640 Gbit/s using a non-linear polarisation-rotating fibre loop [3]. Previously, we have proposed a method for performing the entire TADM operation in a single step using a NOLM, by achieving both the drop- and add-operation simultaneously by cross-phase modulation (XPM) with a single control signal, and this was demonstrated at 320 Gbit/s [4]. In this paper, error-free operation at 640 Gbit/s is shown.

II. PRINCIPLE AND EXPERIMENTAL SET-UP

The experimental set-up for simultaneous TADM at 640 Gbit/s using the NOLM is shown in Figure 1. The NOLM has previously been used for TADM by using the device for the drop- and clear-operations (using XPM by a control signal), followed by the addition of a new data-channel into the cleared time-slot using a (passive) coupler [5]. In this paper, the add-operation is incorporated into the NOLM by injecting the add-channel into the second (right) NOLM input port, as shown in Figure 1. A more detailed explanation of the working principle can be found in [4]. The output 640 Gbit/s data of the TADM with the added channel is demultiplexed in a standard NOLM (DEMUX) to enable detection and subsequent bit error-rate (BER) evaluation.

The data transmitter is shown in Figure 2. A 10 GHz erbium glass oscillating laser (ERGO) emits ~ 2 ps pulses

Fig. 1. Experimental set-up for 640 Gbit/s TADM with simultaneous add and drop-operations using the NOLM (BPF: optical band-pass filter).

Fig. 2. Transmitter of 640 Gbit/s OTDM data and the 10 Gbit/s add-channel. The generated signals are directed to the set-up as shown in Figure 1.

at $\lambda_{data} = 1557$ nm, which are data-modulated by on-off keying (OOK) with a $2^7 - 1$ PRBS pattern. The resulting 10 Gbit/s pulses are split and used to obtain both the 640 Gbit/s data and the 10 Gbit/s add-channel. The 640 Gbit/s data are generated using $2^7 - 1$ PRBS maintaining delay-line multiplexer stages (MUX). The pulse compressors are based on chirping and spectral broadening by self-phase modulation

Fig. 3. Cross-correlations of the 640 Gbit/s data at the output of the TADM.

in a (negative) dispersion-flattened highly non-linear fibre (DF-HNLF), followed by off-carrier filtering. The control pulses for the TADM and DEMUX are obtained from another 10 GHz ERGO laser at $\lambda_{ctrl} = 1542$ nm (not shown). The full-width at half maximum (FWHM) pulse widths at the input to the HNLF in the NOLM (TADM) are noted in Figure 1. The 50 m HNLF in the TADM has non-linear coefficient $\gamma = 10.5$ $W^{-1}km^{-1}$, zero-dispersion wavelength $\lambda_0 \sim 1552$ nm and dispersion slope 0.018 $ps\cdot nm^{-2}km^{-1}$ at 1550 nm. The 30 m HNLF in the NOLM (DEMUX) has similar characteristics.

III. RESULTS

The simultaneous TADM operation of the NOLM at 640 Gbit/s is successful with error-free performance. The cross-correlations of the 640 Gbit/s data in Figure 3 show that the NOLM (TADM) is able to successfully clear the target time-slot (middle trace), and switch the add-channel into the cleared time-slot with the correct timing and amplitude (bottom trace). The BER measurements of the dropped channel are shown in Figure 4 (a). When the add-channel is off, the sensitivity is -31.3 dBm. There is a penalty of 4.4 dB compared to the sensitivity of -35.7 dBm obtained when the add-channel is on, which is due to unsuppressed add-channel light leading to interferometric cross-talk. The BER curve of the added channel after demultiplexing is shown in Figure 4 (b). The sensitivity is -33.0 dBm, which is an improvement of 1.2 dB compared to the original target channel sensitivity of -31.8 dBm. This effect is partly attributed to the slightly wide TADM control pulse FWHM of 1.24 ps compared to the ~ 1.56 ps time slot at 640 Gbit/s. The control pulses therefore suppress the tails of the neighbouring pulses to the target channel, resulting in a broader effective time-slot for the added channel. Figure 4 (c) shows the sensitivities of the demultiplexed target/added channel as well as 6 neighbour channels, both with and without add-drop operation. Error-free performance is obtained in all cases, but add-drop induced penalties can be observed on the nearest add-channel neighbours. This is attributed to a deterioration caused by the wide TADM control pulses, as discussed above. In general, an unstable BER performance was observed during add-

Fig. 4. Results. BER curves of: (a) dropped channel with add-ch on/off, (b) target/added channel after DEMUX. (c) Sensitivities of demultiplexed channels (sensitivity is received power for BER = 10^{-9}).

drop operation (compared to w/o add-drop), which is mainly attributed to unsuppressed TADM-control light overlapping with the data spectrum. Better stability and smaller add-drop penalties are expected by using optimised control pulses and improved filtering.

IV. CONCLUSION

Error-free 640 Gbit/s TADM with simultaneous add- and drop-operations was demonstrated using a NOLM with 50 m HNLF. The add-operation is performed with a negative penalty of -1.2 dB, but some deterioration is observed on the neighbour channels and the dropped channel. Improved results are expected using optimised control pulses and filtering.

REFERENCES

- [1] C. Schubert, C. Schmidt-Langhorst, K. Schulze, V. Marembert, and H. G. Weber, "Time division add-drop multiplexing up to 320 Gbit/s," in *Technical Digest Optical Fiber Communication Conference, OFC'05*, Anaheim, California, U.S.A., Mar. 2005, paper OThN2.
- [2] E. J. M. Verdurmen, J. P. Turkiewicz, E. Tangdionga, G. D. Khoe, and H. de Waardt, "Towards all-optical 320 Gb/s add-drop multiplexing using a nonlinear optical loop mirror," in *Proceedings European Conference on Optical Communication, ECOC'05*, Glasgow, Scotland, Sep. 2005, paper Th3.1.7.
- [3] H. C. H. Mulvad, M. Galili, L. Grüner-Nielsen, L. K. Oxenløwe, A. T. Clausen, and P. Jeppesen, "640 Gbit/s time-division add-drop multiplexing using a non-linear polarisation-rotating fibre loop," in *Proceedings European Conference on Optical Communication, ECOC'08*, Brussels, Belgium, Sep. 2008, paper Tu.3.D.6.
- [4] H. C. H. Mulvad, L. K. Oxenløwe, A. T. Clausen, M. Galili, L. Grüner-Nielsen, and P. Jeppesen, "Error-free 320 Gb/s simultaneous add-drop multiplexing," in *Technical Digest Optical Fiber Communication Conference, OFC'07*, Anaheim, California, U.S.A., Mar. 2007, paper OTu15.
- [5] J. H. Lee, T. Tanemura, Y. Takushima, and K. Kikuchi, "All-optical 80-Gb/s add-drop multiplexer using fiber-based nonlinear optical loop mirror," *IEEE Photonics Technology Letters*, vol. 17, no. 4, pp. 840–842, 2005.