640 Gbit/s time-division add-drop multiplexing using a non-linear polarisation-rotating fibre loop

Mulvad, Hans Christian Hansen; Galili, Michael; Grüner-Nielsen, Lars; Oxenløwe, Leif Katsuo; Clausen, Anders; Jeppesen, Palle

Published in:
European Conference on Optical Communication

Link to article, DOI:
[10.1109/ECOC.2008.4729220](https://doi.org/10.1109/ECOC.2008.4729220)

Publication date:
2008

Document Version
Publisher's PDF, also known as Version of record

[Link back to DTU Orbit](#)

Citation (APA):
Mulvad, H. C. H., Galili, M., Grüner-Nielsen, L., Oxenløwe, L. K., Clausen, A., & Jeppesen, P. (2008). 640 Gbit/s time-division add-drop multiplexing using a non-linear polarisation-rotating fibre loop. In *European Conference on Optical Communication* (pp. 1-2). IEEE. <https://doi.org/10.1109/ECOC.2008.4729220>

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

640 Gbit/s Time-Division Add-Drop Multiplexing using a Non-Linear Polarisation-Rotating Fibre Loop

H.C.H. Mulvad (1), M. Galili (1), L. Grüner-Nielsen (2), L.K. Oxenløwe (1), A.T. Clausen (1), and P. Jeppesen (1)

1 : Department of Photonics Engineering, Technical University of Denmark, DK-2800 Kgs. Lyngby, Denmark

e-mail: hchm@com.dtu.dk

2 : OFS Fitel Denmark ApS, Priorparken 680, DK-2605 Brøndby, Denmark

Abstract

We report the first demonstration of error-free 640 Gbit/s time-division add-drop multiplexing, performed by non-linear polarisation-rotation using a loop with a polarisation-maintaining HNLF.

Introduction

Time-division add-drop multiplexing (TADM) is the switching functionality where data pulses are extracted and replaced in a serial data stream. A possible application is in optical time-division multiplexed (OTDM) systems, where the data signals are formed by bit-interleaving narrow-pulse, identical-wavelength data channels at a low base rate (e.g. 10 Gbit/s), enabling aggregate bitrates currently up to 640 Gbit/s. Fibre-based switches are the most promising candidates for TADM at ultra-high bitrates, since they are based on the Kerr non-linearity with a response time of a few fs, which prevents data-pattern dependence. Fibre-based TADM switches have previously been demonstrated using Kerr shutters at 160 Gbit/s [1,2], and with non-linear optical loop mirrors at 160 Gbit/s [3] and 320 Gbit/s [4].

Here, we report on the first demonstration of TADM of a 640 Gbit/s OTDM data signal, using a new non-linear polarisation-rotating loop (PRL), which is a looped version of the Kerr shutter, containing a 94 m elliptical core polarisation-maintaining highly non-linear fibre (PM-HNLF) [5]. This switch makes it possible to simultaneously drop a data-channel and clear the corresponding bit-slot, enabling a new channel to be coupled into the output OTDM data. Bit-error rate (BER) measurements show error-free performance, including a low penalty imposed on the added channel.

Principle and experimental set-up

The experimental set-up is shown in Fig. 1(a), covering the TADM with separate drop-operation (*DROP*) and add-operation (*ADD*), followed by a demultiplexer (*DEMUX*). The drop-operation is performed using the PRL, followed by a polarising beam splitter (PBS2). The PRL is formed by a loop connecting the two outputs of PBS1. The entire loop is built from polarisation-maintaining (PM) components, which results in increased stability and avoids an internal polarisation controller. All signals propagate along the slow axis. High-intensity 10 GHz control pulses are coupled into the slow axis of the loop via a PM 3 dB coupler, and are blocked after the

PM-HNLF by a 15 nm PM bandpass filter (BPF). The 94 m PM-HNLF has dispersion 0.13 ps/(nm·km) and slope 0.027 ps/(nm²·km) at 1550 nm, and non-linear coefficient $\gamma \sim 10 \text{ W}^{-1}\text{km}^{-1}$.

(a) Add-drop multiplexer and demultiplexer

(b) Transmitter: 640 Gbit/s data and 10 Gbit/s add-ch.

Figure 1: Experimental set-up.

The working principle of the PRL is briefly described in the following. The polarisation of the incoming OTDM signal is set to a linear state at a 45° angle to the principal axis of PBS1. It is then split into two field-components $E^{\parallel}$ and $E^{\perp}$ with equal amplitude, with $E^{\parallel}$ propagating in the clockwise (c-w) direction of the PRL, and $E^{\perp}$ in the counter-clockwise (c-c-w) direction. A phase-shift of π is then imposed on the $E^{\parallel}$ -component of the channel to be dropped (target channel), achieved by cross-phase modulation (XPM) from the control pulses inside the PM-HNLF. When $E^{\parallel}$ and $E^{\perp}$ are recombined again at PBS1, the XPM-induced π -phaseshift on the $E^{\parallel}$ -component of the target ch causes its polarisation-state to be rotated by 90° compared to the other data-channels. This enables the target ch to be completely extracted by

PBS2, which simultaneously clears the corresponding bit-slots in the OTDM signal (*DROP*). This allows a 10 Gbit/s add-channel to be coupled into the OTDM signal by a 3 dB coupler, followed by a polarizer to ensure identical polarisations (*ADD*). After the add-operation, the OTDM signal is demultiplexed (*DEMUX*) in a non-linear optical loop mirror (NOLM) for BER characterisation.

The transmitter for data pulses is shown in Fig. 1 (b). A 10 GHz erbium glass oscillating laser (ERGO) emits ~2 ps pulses at 1557 nm, which are data-modulated by on-off keying with a 2^7-1 PRBS pattern. The resulting 10 Gbit/s pulses are split and used to generate both the 640 Gbit/s data and the 10 Gbit/s add-channel. The 640 Gbit/s data are generated using 2^7-1 PRBS maintaining delay-line multiplexer stages (MUX), with an intermediate pulse compressor. The 10 Gbit/s add-channel pulses are compressed, followed by a variable attenuator and time-delay to ensure the correct amplitude and timing before the add-operation. Control pulses are obtained from another 10 GHz ERGO laser at 1542 nm (synchronised by the 1557 nm ERGO). These pulses are compressed, split and then separately BPF-filtered and amplified before being used as control for the PRL and NOLM (not shown). All pulse compressors are based on chirping and spectral broadening by self-phase modulation in a (negative) dispersion-flattened HNLF (DF-HNLF). All relevant pulse FWHM widths, wavelengths and average powers are shown in Fig. 1, and pulse characterisations are found in Fig. 2 (a) and (b).

Figure 2: Pulse characterisations. (a), (c) cross-correlations, (b) autocorrelations, (d) eye diagrams.

Results

The add-drop operation is successful with error-free performance. Fig. 2 (c) shows cross correlations of the 640 Gbit/s data after the TADM. The top trace is without (w/o) add-drop operation. When the PRL ctrl pulses are on, the target ch is dropped at PBS2, leaving a cleared bit-slot (middle trace), into which the add-ch is then coupled (bottom trace). Fig. 2 (d)

shows simultaneously open eye diagrams for both the dropped and demultiplexed added ch.

Fig. 3 shows the BER measurements. The 640 Gbit/s data are demultiplexed in two situations: with add-drop operation (w add-drop), and w/o add-drop operation, corresponding to the bottom and top traces of Fig. 2 (c). In Fig. 3 are shown BER curves for the target/added channel (b), its left (a) and right (c) neighbour channels. Fig. 3 (e) shows the obtained sensitivities of the target/added ch and 8 neighb. channels. The corresponding add-drop induced penalties are shown in Fig. 3 (f). The added ch suffers only a 1.1 dB penalty compared to the target ch. The left neighb. suffers a 2.3 dB penalty, which is mainly attributed to a small asymmetric pedestal of the added ch, and not the switching in the PRL. This penalty can thus be avoided by using e.g. a pedestal-suppression technique. The right neighb., as well as the remaining channels are practically unaffected, with penalties < 0.4 dB. The BER performance of the dropped ch. is error-free with a sensitivity of -32.1 dBm, as shown in Fig. 3 (d).

Figure 3: BER measurements

Conclusions

We have demonstrated time-division add-drop multiplexing at the record-high bitrate of 640 Gbit/s, using a new non-linear polarisation-rotating loop with a PM-HNLF. BER measurements showed error-free performance with only 1.1 dB add-drop penalty on the added channel.

References

1. C. Schubert et al OFC'05 (2005), paper OThN2
2. J.H. Lee et al Optics Express, Vol. 13 No. 18 (2005), pp. 6864-6869
3. E.J.M. Verdurmen et al ECOC'05 (2005), Th 3.1.7
4. H.C.H. Mulvad et al OFC'07 (2007), paper OTu15
5. L. Grüner-Nielsen et al subm. to ECOC'08 (2008)