160 Gb/s Raman-assisted notch-filtered XPM wavelength conversion and transmission

Galili, Michael; Oxenløwe, Leif Katsuo; Mulvad, Hans Christian Hansen; Zibar, Darko; Clausen, Anders; Jeppesen, Palle

Published in:
2006 Optical Fiber Communication Conference/national Fiber Optic Engineers Conference, Vols 1-6

Publication date:
2007

Document Version
Publisher's PDF, also known as Version of record

[Link back to DTU Orbit](#)

Citation (APA):
Galili, M., Oxenløwe, L. K., Mulvad, H. C. H., Zibar, D., Clausen, A., & Jeppesen, P. (2007). 160 Gb/s Raman-assisted notch-filtered XPM wavelength conversion and transmission. *2006 Optical Fiber Communication Conference/national Fiber Optic Engineers Conference, Vols 1-6*, 1125-1127.

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

combined with a CW probe at 1544 nm. Wavelength conversion by XPM is performed in 500 m of Highly Non-Linear Fibre (HNLF) with $\gamma \sim 10 \text{ W}^{-1} \text{ km}^{-1}$, zero dispersion wavelength $\lambda_0 \sim 1551 \text{ nm}$ and $S \sim 0.017 \text{ ps/nm}^2 \text{ km}$. The converted signal is extracted using a combination of a 3.2 nm notch filter centred at 1545.5 nm and a 3 nm tunable band pass filter at the output of the HNLF. A counter propagating Raman pump (1450 nm and $\sim 31 \text{ dBm}$) in the HNLF supplies Raman gain to assist the XPM. The wavelengths of the CW probe and the data signal are placed nearly symmetrically around λ_0 to reduce the group velocity dispersion induced walk-off between the two signals to $\sim 0.1 \text{ ps}$ in the HNLF.

After wavelength conversion and retransmission the converted data signal is demultiplexed in a Non-linear Optical Loop Mirror (NOLM) using the transmitted control pulses which are also used to generate an electrical clock signal for synchronising the receiver electronics to the transmitted data. In this way a simple setup for characterising a high-speed system and transmission has been realised using a single pulse source and a simple demultiplexer.

3. Results of Raman-assisted XPM wavelength conversion and transmission

In the HNLF in the setup described above spectral sidebands were generated on the CW probe due to XPM by co-propagating data marks in the amplified 160 Gb/s data signal. Thus the spectral sidebands contain the intensity modulation of the input signal and can be extracted as a wavelength converted output. Due to a phase mismatch between the two sidebands one of them must be suppressed along with the probe in order to reduce noise in the output signal [7]. Fig. 2 shows the spectrum of the wavelength converted 160 Gb/s signal where the notch filter and band pass filter are used to suppress the CW probe, the higher wavelength sideband and the original data signal. The spectra clearly show a reduction in the noise level of $\sim 5 \text{ dB}$ when applying Raman gain to the conversion process.

Fig. 2 Spectrum of the wavelength converted signal with and without Raman gain

In-line notch-filtered Raman-assisted XPM wavelength conversion has been achieved in a 160 Gb/s transmission setup. Two different configurations for transmission have been investigated. In one case the 160 Gb/s data was transmitted 80 km and then wavelength converted before being detected in the receiver. In the other case the converted signal was transmitted another 50 km, i.e. for a total transmission of 130 km, before it was received. Fig. 3a shows the BER measurements of the transmitted signals. For the 80 km transmission BER curves are shown for both cases of wavelength conversion with and without Raman gain to assist the XPM process. It is seen that using Raman gain in the conversion improves the BER sensitivity by $\sim 0.7 \text{ dB}$ in this case. It is also seen that the transmitted and converted 160 Gb/s signal (Fig. 3b upper) has clear eye openings and that the 10 GHz electrical sine clock extracted from the transmitted control pulses contains very little noise. All the 16 10 Gb/s tributary channels are seen to achieve error free performance within a 3.1 dB range of receiver power at BER 10^{-9} (Fig. 3c upper). The first channels overlap partially in time with the transmitted control signal and this is believed to be the cause of the reduced sensitivity compared to the remaining channels due to transfer of power between the two polarisations and limited isolation in the PBS ($\sim 20 \text{ dB}$). Transmitting the converted signal an additional 50 km before demultiplexing and detecting it induces a $\sim 2 \text{ dB}$ sensitivity penalty (Fig. 3a) and both the 160 Gb/s eye and the extracted electrical 10 GHz clock contain more noise than in the case of no transmission after conversion (Fig. 3b lower). Despite the added noise 15 of the 16 transmitted channels show error free performance within 4.5 dB receiver power range (Fig. 3c lower).

Fig. 3 (a) Shows BER measurements for different configurations of transmission and wavelength conversion. (b) Wavelength converted 160 Gb/s eye diagram and transmitted 10GHz control signal for 80 km transmission (upper) and 130 km transmission (lower). (c) Channel receiver sensitivities for 80 km transmission (upper) and 130 km transmission (lower)

The channel overlapping with the transmitted control pulse could no longer achieve error free operation. From the sensitivity measurements it is seen that applying Raman gain to assist the XPM conversion improves the receiver sensitivity of 11 of the 16 channels ($\sim 70\%$).

Fig. 4 Autocorrelations and pulse widths of: (a) data signal after 80 km transmission and conversion (b) data signal transmitted additional 50 km after conversion (c) 10 GHz control pulses transmitted 130 km

Autocorrelation of the wavelength converted data signal after 80 km transmission (Fig. 4a) shows no pulse broadening in the transmitted and converted signal compared to the 2 ps input pulses and only a very small pulse overlap can be seen. Transmitting another 50 km after conversion (Fig. 4b) introduces some pulse broadening ~ 0.5 ps and this in turn causes increased pulse overlap as seen from the autocorrelation. This pulse broadening is expected to be due to slight chirping of the pulses by the applied filtering scheme in the wavelength converter. The transmitted control signal (Fig. 4c) shows virtually no pulse broadening after 130 km transmission and is suitable for demultiplexing in the receiver.

4. Conclusion

This paper has demonstrated Raman-assisted notch-filtered XPM for in-line wavelength conversion in a 160 Gb/s transmission system spanning a total distance of 130 km. Error free operation was achieved for all channels except the one overlapping with the transmitted control signal required for this simplified characterisation setup. A noise reduction from applying Raman gain to the conversion and its improvement on system performance is characterised.

References

- [1] P. Winzer, et al., "107-Gb/s optical ETDM transmitter for 100G Ethernet transport," in *Proc. of ECOC*, Th4.1.1 (2005)
- [2] W. Wang, et al., "All-Optical Label Switching/Swapping of 160 Gbps Variable Length packets and 10 Gbps Labels using a WDM Raman Enhanced-XPM Fiber Wavelength Converter with Unicast/Multicast Operation," in *Proc. of OFC*, PDP8 (2004).
- [3] M. Galili, et al., "160 Gb/s Raman-Assisted SPM Wavelength Converter," in *Proc. of ECOC*, Th4.3.1, (2004)
- [4] S. Watanabe et al., "160 Gb/s Optical 3R-Regenerator in Fiber Transmission experiment," in *Proc. of OFC*, PD16-1 (2003)
- [5] S. Nakamura et al., "168 Gb/s all-optical wavelength conversion with a symmetric-Mach-Zender-type switch," *IEEE Photon. Technol. Lett.* **13**(10), 1091 (2001)
- [6] M. Galili et al., "160 Gb/s Notch-Filtered Raman-Assisted XPM Wavelength Converter," in *Proc. of ECOC*, Mo4.5.3 (2005)
- [7] M. Galili et al., "Characterisation of Systems for Raman-Assisted High-Speed Wavelength Conversion," in *Proc. of CLEO*, CMQ2 (2005)