Nonlinear H-infinity state feedback controllers: computation of valid region

Cromme, Marc; Møller-Pedersen, Jens; Pagh Petersen, Martin

Published in:
Proceedings of the 1997 American Control Conference

Link to article, DOI:
[10.1109/ACC.1997.611825](https://doi.org/10.1109/ACC.1997.611825)

Publication date:
1997

Document Version
Publisher's PDF, also known as Version of record

[Link back to DTU Orbit](#)

Citation (APA):
Cromme, M., Møller-Pedersen, J., & Pagh Petersen, M. (1997). Nonlinear H-infinity state feedback controllers: computation of valid region. In *Proceedings of the 1997 American Control Conference* (Vol. 1, pp. 391-395). IEEE. <https://doi.org/10.1109/ACC.1997.611825>

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

Nonlinear H_∞ state feedback controllers: computation of valid region

Marc Cromme
 Dep. of Mathematics
 Tech. Univ. of Denmark
 2800 Lyngby, Denmark
 marc@mat.dtu.dk
 http://www.mat.dtu.dk

Jens Møller-Pedersen
 TetraPlan ApS
 Badstuestræde 8, 3th floor
 1209 Copenhagen K
 Denmark
 jmp@tetraplan.dk

Martin Pagh Petersen
 The Danish Road Directorate
 Ministry of Transport
 Niels Juels Gade 13
 1020 Copenhagen K
 mpp@vd.dk

Keywords:

regional (semi-global) stabilizing nonlinear H_∞ control, Luke's approximation scheme, implementation in MAPLE

Abstract

"From a general point of view the state feedback H_∞ suboptimal control problem is reasonable well-understood. Important problems remain with regard to a priori information of the size of the neighbourhood where the local state feedback H_∞ problem is solvable, and with regard to the nature of solutions V to the Hamilton-Jacobi inequalities ... such as properness of V as a candidate Lyapunov function" Citation van der Schaft, 1992 [vdS92].

The first of these problems is solved regionally (semi-globally) in this paper, and the obtained control laws are implemented in MAPLE.

1. Introduction

The local nonlinear state feedback H_∞ control problem has been solved in the early nineties. Van der Schaft [vdS92] describes the solution process for affine systems using the theory of dissipative systems first introduced by Willems [Wil72]. Isidori [Isi92], and Isidori and Astolfi [IA92b], [IA92a] approach the problem by the theory of differential games. The problem has been solved for more general nonlinear plants by Isidori and Kang [IK95], and Ball, Helton, and Walker [BHW93]. Lukes approximation scheme [Luk69] has been used to compute solutions of the Hamilton-Jacobi inequalities of the local nonlinear state feedback H_∞ control problem [IK95], [MP95].

From an engineering point of view all these results are insufficient: local control laws are found without any knowledge of boundedness of the closed loop state trajectories, or the size and shape of the neighbourhood where state feedback control works as intended.

State boundedness is an indispensable property of controlled systems for two reasons: state blow-up leads usually to plant or control system failure or damaging, and local control is certainly not applicable when the bound on state trajectories is not known a priori.

The size and shape of the neighbourhood where the implemented control law is meaningful are important design parameters for any practical control purpose. If they do not cover the intended performance envelope of the plant, another control strategy must be chosen.

Finally, any practical oriented control law should allow for inaccurate setting of initial conditions. This kind of initial value robustness may be very important when calculating the secure performance envelope of a closed loop control system.

In the following, given a particular solution V of the Hamilton-Jacobi inequality of concern, any compact neighbourhood $\Omega \subset \mathbb{R}^m$ of the equilibrium point which has these beneficial properties is called a **valid region**. We assume without loss of generality that the equilibrium point of concern is at the origin. Moreover, a class of disturbances such that some given Ω is a valid region, is called **valid disturbance set**, and it is denoted $\mathbf{W}^\epsilon$. A set of initial conditions, denoted $\Omega^\epsilon \subset \Omega$, is called **valid initial set** if all state trajectories driven by valid disturbances renders Ω a valid region. The problem addressed here is:

1.1 Problem Formulation Given a nonlinear state feedback H_∞ control problem and a formal solution V to the associated Hamilton-Jacobi inequality, find a valid region Ω , a valid disturbance set $\mathbf{W}^\epsilon$, and a valid initial set $\Omega^\epsilon \subset \Omega$ such that every state trajectory $x(\cdot)$ with initial condition $x_0 \in \Omega^\epsilon$ subject to disturbances $w(\cdot) \in \mathbf{W}^\epsilon$ satisfies an L_2 gain less than or equal γ , and approaches the origin as time goes to infinity.

2. Local H_∞ state feedback control

Let $\mathbb{R}^+$ denote the real positive closed time axis $[0, \infty[$. In general we consider the plant

$$\dot{x} = X(x, u, w) \quad , \quad z = Z(x, u) \quad (1)$$

where $x(\cdot) : \mathbb{R}^+ \mapsto \mathbb{R}^m$ is called the state, $u(\cdot) : \mathbb{R}^+ \mapsto \mathbb{R}^l$ the input, $w(\cdot) : \mathbb{R}^+ \mapsto \mathbb{R}^n$ the exogenous input, also called disturbance, and $z(\cdot) : \mathbb{R}^+ \mapsto \mathbb{R}^p$ the performance,

or to be controlled signal. The symbol $X(x, u, w)$ denotes a smooth vector field on $\mathbb{R}^m$, and the vector valued function $Z(x, u)$ specifies smoothly the performance measure. We assume the equilibrium conditions $X(0, 0, 0) = 0$ and $Z(0, 0) = 0$ to hold.

The open loop system $\dot{x} = X^{\text{open}}(x, w) \equiv X(x, 0, w)$ subject $w(\cdot) = 0$ is autonomous, and by assumption the origin is an equilibrium point, hence an invariant set. The static feedback control is given by some vector valued function $a : \mathbb{R}^m \mapsto \mathbb{R}^l$, $u = a(x)$, where $a(0) = 0$ is assumed in order to preserve the equilibrium point zero. The closed loop system is given by the equations

$$\dot{x} = X(x, a(x), w) \quad , \quad z = Z(x, a(x)) \quad . \quad (2)$$

Whenever convenient, we use the notation $x(\cdot)$ for the signal $x(\cdot, t_0, x_0, u(\cdot), w(\cdot))$. It is assumed that all signals are L_2^{loc} , and that the state exist uniquely for all input, and is a C^1 signal.

Let $\|\cdot\|$ denote the usual Euclidean norm on the Banach space $\mathbb{R}^p$, then the L_2 norm of any locally square integrable signal $y(\cdot) : \mathbb{R}^+ \mapsto \mathbb{R}^p$, $p \in \mathbb{N}$ is for all $T \in \mathbb{R}^+$ defined

$$\|y\|_T^2 \equiv \int_0^T |y(t)|^2 dt \quad , \quad (3)$$

and the closed loop system (2) has by definition local L_2 gain less than or equal $\gamma \geq 0$ if

$$\|z\|_T^2 \leq \gamma^2 \|w\|_T^2 + V_a(x_0) \quad (4)$$

for all $w(\cdot), z(\cdot) \in L_2^{\text{loc}}$, all $T \in \mathbb{R}^+$ and all initial conditions $x_0 \in \mathbb{R}^m$ such that the state trajectories never leave Ω . Here the available storage $V_a : \mathbb{R}^m \mapsto [0, \infty[$ is a non-negative and bounded function with minimum $V_a(0) = 0$ at the origin [vdS92], [IA92a].

It is known [vdS92] that the local L_2 gain condition is implied by the existence of a non-negative, bounded C^1 storage function $V : \Omega \mapsto [0, \infty[$ satisfying the closed loop differential dissipation inequality

$$\begin{aligned} \mathbf{H}_\gamma(u, w) &\equiv \frac{d}{dt} V - (\gamma^2 |w|^2 - |z|^2) \\ &= \frac{\partial V}{\partial x} X(x, u, w) \\ &\quad - \gamma^2 |w|^2 + |Z(x, u)|^2 \leq 0 \end{aligned} \quad (5)$$

for all $t \in \mathbb{R}^+$, where the Hamiltonian function $\mathbf{H}_\gamma$ is defined by equation (5). Assuming that $Z(x, u)$ is such that $\frac{\partial Z}{\partial u}(0, 0)$ has rank l , it is known [IK95] that $\mathbf{H}_\gamma$ has a unique saddle point $(u_{\min}, w_{\max})$ for all x and all $\frac{\partial V}{\partial x}$ near zero, and the extremal functions $u_{\min}(x, \frac{\partial V}{\partial x})$, $w_{\max}(x, \frac{\partial V}{\partial x})$ are characterized by the equations

$$\begin{aligned} \frac{\partial \mathbf{H}_\gamma}{\partial u}(u_{\min}, w_{\max}) &= 0 \quad , \quad u_{\min}(0, 0) = 0 \\ \frac{\partial \mathbf{H}_\gamma}{\partial w}(u_{\min}, w_{\max}) &= 0 \quad , \quad w_{\max}(0, 0) = 0 \end{aligned} \quad (6)$$

We deduce by the saddle point property (6) that $u_{\min}$ and $w_{\max}$ are the best possible state feedback law and the worst possible disturbance respectively.

Hence, we seek for a sufficient small $\gamma \geq 0$, and a C^1 storage function V defined on a sufficient big neighbourhood Ω around the origin satisfying the Hamilton-Jacobi inequality [IK95]

$$\begin{aligned} \min_{\gamma} \mathbf{H}_\gamma^{\max}(x, \frac{\partial V}{\partial x}) &= \frac{\partial V}{\partial x} X(x, u_{\min}(x, \frac{\partial V}{\partial x}), w_{\max}(x, \frac{\partial V}{\partial x})) \\ &\quad - \gamma^2 |w_{\max}(x, \frac{\partial V}{\partial x})|^2 + |Z(x, u_{\min}(x, \frac{\partial V}{\partial x}))|^2 \\ &\leq 0 \quad \text{for all } x \in \Omega \quad . \end{aligned} \quad (7)$$

This problem can be solved locally by an polynomial expansion algorithm due to Lukes [Luk69].

In the case of input affine systems

$$\begin{aligned} \dot{x} &= A(x) + B_u(x)u + B_w(x)w \\ z &= C(x) + D(x)u \quad , \end{aligned} \quad (8)$$

(here we have $A(0) = 0$ and $C(0) = 0$) satisfying $D^T D > 0$ for all x , the worst case disturbance and the minimizing input can be found completing the squares, they are for all x and $\frac{\partial V}{\partial x}$ given by the expressions [Isi92]

$$\begin{aligned} u_{\min} &= -(D^T D)^{-1} (\frac{1}{2} B_u^T \frac{\partial V}{\partial x} + D^T C) \quad , \\ w_{\max} &= \frac{1}{2\gamma^2} B_w^T \frac{\partial V}{\partial x} \quad . \end{aligned} \quad (9)$$

Here we seek for a sufficient small $\gamma \geq 0$, and a C^1 storage function V defined on a sufficient big neighbourhood Ω around the origin satisfying the Hamilton-Jacobi inequality [Isi92]

$$\begin{aligned} \min_{\gamma} \mathbf{H}_\gamma^{\max}(\frac{\partial V}{\partial x}, x) &= \frac{\partial V}{\partial x} Q(x) \frac{\partial V}{\partial x}^T + \frac{\partial V}{\partial x} L(x) + K(x) \\ &\leq 0 \quad \text{for all } x \in \Omega \quad , \end{aligned} \quad (10)$$

where the quadratic term $Q(x)$, the linear term $L(x)$, and the constant term $K(x)$ are defined

$$\begin{aligned} Q(x) &\equiv \frac{1}{4\gamma^2} B_w B_w^T - \frac{1}{4} B_u (D^T D)^{-1} B_u^T \\ L(x) &\equiv A - B_u (D^T D)^{-1} D^T C \\ K(x) &\equiv C^T (I - D (D^T D)^{-1} D^T) C \quad . \end{aligned} \quad (11)$$

The existence of a C^1 storage function satisfying (7) or (10) locally guarantees that the input-output map of the closed loop system has L_2 gain less than or equal γ as defined in equation (4) *if and only if every closed loop trajectory is bounded inside Ω* . Unfortunately, we do not have any priory estimates on the boundedness or on the asymptotic behaviour of the state.

We will impose in the following a detectability assumption on the system: The control system (1) is **zero-detectable** if all bounded trajectories $x(\cdot)$ subject $w(\cdot) = 0$ generating the zero-output $z(\cdot) = 0$ are approaching the origin as $t \rightarrow \infty$.

Figure 1: Boundedness of state, asymptotic stability

3. Regional H_∞ control

A set $M \subset \mathbb{R}^m$ is **positive invariant** with respect to the autonomous system (2) if all trajectories starting in M are defined in the future and never leave M as time increases. It is **invariant** if $x(\cdot)$ defined in future and past, and evolves entirely in M .

It is our purpose to use a formal solution to the Hamilton-Jacobi inequality as a Lyapunov function in order to establish regional stability properties of the H_∞ state feedback problem. Our new theorem is inspired on the proof of the well known La Salle invariance principle for autonomous systems [SL61], which is connecting the existence of a C^1 Lyapunov function $V : \mathbb{R}^m \mapsto \mathbb{R}$ with bounded and connected pre-image $\Omega \equiv V^{-1}([-\infty, c])$ satisfying $\frac{\partial V}{\partial t} V \leq 0$, with the positive invariance of Ω and the asymptotic stability property of largest invariant set contained in the set where $\frac{\partial V}{\partial t} V = 0$.

In order to prove the boundedness of state trajectories we have to restrict ourselves to the class of disturbances

$$\mathbf{W}^\epsilon \equiv \left\{ w(\cdot) \in L_2(\mathbb{R}^+) \mid \|w\|_2^2 \leq \epsilon \right\} . \quad (12)$$

Given some solution V to the standard H_∞ Hamilton-Jacobi inequality, the following new lemma will help us to construct the valid sets (left part of figure 1). The lemma is proved in [CMPP96].

3.1 Lemma Given a formal C^1 solution V of the Hamilton-Jacobi inequality (7) or (10), assume that some component of $V^{-1}([-\infty, c_\Omega])$, $c_\Omega \in \mathbb{R}$, denoted Ω , is connected and bounded.

Then Ω is compact and closed loop positive invariant by use of the state feedback law $a(x) = u_{\min}(x)$ subject to the condition $w(\cdot) = 0$.

Pick some $\epsilon < c_\Omega$, then the appropriate subset $\Omega^\epsilon \subset \Omega$ of $V^{-1}([-\infty, c_\Omega - \epsilon])$ is such that any closed loop trajectory $x(\cdot)$ with initial condition $x_0 \in \Omega^\epsilon$ is bounded inside Ω if driven by the state feedback law $a(x) = u_{\min}(x)$, and by any disturbance $w(\cdot) \in \mathbf{W}^\epsilon$.

Following the principal idea of the paper [IK95] as outlined in section 2., we conclude that any C^1 function V satisfying the Hamilton-Jacobi inequality (7) will also satisfy the L_2 gain (4) in case that the state is bounded inside Ω . We take advantage of lemma 3.1 to state the following theorem, and to follow the above explained ideas to proof it. The proof is found in appendix A.

3.2 Theorem Assume that some C^1 solution $V : \Omega \mapsto \mathbb{R}$ of the Hamilton-Jacobi inequality (7) is defined on a bounded and connected component Ω of $V^{-1}([-\infty, c_\Omega])$, $c_\Omega \in \mathbb{R}$. Assume furthermore that $\frac{\partial V}{\partial u}(0, 0)$ has rank l .

Then all closed loop trajectories $x(\cdot)$ subject $a(x) = u_{\min}(x)$ with initial condition $x_0 \in \Omega^\epsilon$ do not leave Ω if driven by some $w(\cdot) \in \mathbf{W}^\epsilon$, and the system has L_2 gain less than or equal γ .

Moreover, all such $x(\cdot)$ generated by $w(\cdot) \in \mathbf{W}^\epsilon$ which are identically zero for all times $t > T$, $T \in \mathbb{R}$, approach the biggest closed loop invariant set M contained in the null set

$$\mathbf{N} \equiv \left\{ x \in \Omega \mid H_\gamma^{\min \max}(x, \frac{\partial V}{\partial x}) = 0 \right\} .$$

Assume furthermore that the control system (1) is zero-detectable, then $x(\cdot)$ approaches the origin as $t \rightarrow \infty$.

In other words, given a formal solution V to the associated Hamilton-Jacobi inequality, the valid region Ω is given by some bounded (and connected) component of the pre-image $V^{-1}([-\infty, c])$, the valid disturbance set $\mathbf{W}^\epsilon$ is the set of signals which L_2 norm is bounded by ϵ , and the valid initial set Ω^ϵ is then given by the appropriate component of the pre-image $V^{-1}([-\infty, c - \epsilon])$.

4. Lukes approximation

Local solutions of the Hamilton-Jacobi inequality can be obtained by use of an approximation scheme originally developed by Lukes [Luk69] for quadratic cost functions [IK95]. For computational ease, we discuss in the following sections only affine systems although Lukes approximation method can be used for general nonlinear systems. We use the MAPLE implementation [MP95].

Consider the perturbed Hamilton-Jacobi equation

$$\begin{aligned} H_\gamma^{\min \max}(\frac{\partial V}{\partial x}, x) &= \frac{\partial V}{\partial x} Q(x) \frac{\partial V}{\partial x}^T + \frac{\partial V}{\partial x} L(x) + K(x) \\ &= -\Phi(x) \text{ for all } x \in \Omega , \end{aligned} \quad (13)$$

where $\Phi(x) : \Omega \mapsto \mathbb{R}^+$ is some positive definite perturbation function which we will use as design parameter to style the size and shape of the valid region.

It is easily seen by (8) (11) that $L(x)$ is of least first order, and $K(x)$, $\Phi(x)$ and $V(x)$ of least second. We make the following analytic data expansions $V(x) = x^T V^{[2]} x + \sum_{k=3}^{\infty} V^{[k]}(x)$, $Q(x) = Q^{[0]} + \sum_{k=1}^{\infty} Q^{[k]}(x)$, $L(x) = L^{[1]} x + \sum_{k=2}^{\infty} L^{[k]}(x)$, $K(x) = x^T K^{[2]} x + \sum_{k=3}^{\infty} K^{[k]}(x)$, $\Phi(x) = x^T \Phi^{[2]} x + \sum_{k=3}^{\infty} \Phi^{[k]}(x)$ where $(\cdot)^{[k]}$ denotes k -th order monomials. Then the perturbed Hamilton Jacoby equality (13) can be rewritten

$$\begin{aligned} 0 &= \sum_{m=2}^{\infty} \left[\sum_{k=1}^{m-1} \frac{\partial V}{\partial x} [^{m-k+1}] L^{[k]} + K^{[m]} + \Phi^{[m]} \right. \\ &\quad \left. + \left(\sum_{k=0}^{m-2} \sum_{l=1}^{m-k-1} \frac{\partial V}{\partial x} [^{m-k-l+1}] Q^{[k]} \frac{\partial V}{\partial x} [^{l+1}] \right) \right] . \end{aligned} \quad (14)$$

Note that $\frac{\partial V^{[m]}}{\partial x} \equiv \frac{\partial V^{[m]}}{\partial x}$ are of order $m - 1$.

Isolating the second order terms we find the usual Riccati equation of the linearized and perturbed H_∞ control problem

$$0 = L^{[1]}V^{[2]} + V^{[2]}L^{[1]T} + V^{[2]}Q^{[0]}V^{[2]} + K^{[2]} + \Phi^{[2]} \quad (15)$$

In case that $V^{[2]}$ is a solution of the Riccati equation (15), the second order terms of the perturbed Hamilton-Jacobi equation (14) vanish, and the m order terms can be rearranged

$$\begin{aligned} -\frac{\partial V^{[m]}}{\partial x} (L^{[1]} + Q^{[0]}V^{[2]})x &= \sum_{k=2}^{m-1} \frac{\partial V^{[m-k+1]}}{\partial x} L^{[k]} + K^{[m]} + \Phi^{[m]} \\ &+ \sum_{k=1}^{m-2} \sum_{l=1}^{m-k-1} \left(\frac{\partial V^{[m-k-l+1]}}{\partial x} Q^{[k]} \frac{\partial V^{[l+1]}}{\partial x} \right) \quad (16) \\ &\text{for } m = 3, 4, 5, \dots \end{aligned}$$

Assuming that the linearized problem (15) has a stabilizing solution $V^{[2]}$, the matrix $F = L^{[1]} + Q^{[0]}V^{[2]}$ is positive definite and has therefore an inverse. Consequently, the equations (16) can be solved recursively.

5. Example

The theory developed in the former sections is now illustrated by a simplified two-dimensional example arising in the field of robotics. We consider the plant

$$\begin{aligned} \begin{bmatrix} \dot{x}_1 \\ \dot{x}_2 \end{bmatrix} &= \begin{bmatrix} \sin(x_1) - 2x_2 \\ x_1 \end{bmatrix} + \begin{bmatrix} 1 \\ 0 \end{bmatrix} u + \begin{bmatrix} 1 \\ 0 \end{bmatrix} w \\ z &= \begin{bmatrix} x_2 + x_2^3 \\ x_1 \\ 0 \end{bmatrix} + \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix} u \end{aligned}$$

with equilibrium point zero.

Note that the linearized system is stabilizable by linear feedback, and we want to compare the quality of a linear controller with a third order controller. The optimal feedback L_2 gain is near 1.2, but we use the suboptimal value $\gamma = 2$.

Solving the unperturbed Riccati equation (15) (that is $\Phi = 0$), we find the formal second order storage function

$$V_{\text{lin}}(x) = 0.710x_1^2 + 3.097x_1x_2 + 4.037x_2^2$$

which gives the linear feedback

$$u_{\text{lin}}(x) = -1.421x_1 - 3.097x_2$$

Unfortunately, this storage function satisfies not the Hamilton-Jacobi inequality (7) on a sufficient large area: in figure 2 the set

$$\mathbf{A} \equiv \left\{ x \mid H_{\gamma}^{\min}(x, \frac{\partial V}{\partial x}) < 0 \right\}$$

Figure 2: Unperturbed solution

is depicted grey.

Now perturbing the Riccati equation (15) with $\Phi(x) = 2x_1^2 + x_2^2$ we calculate the formal second order storage function

$$V_{\text{lin,per}}(x) = 0.818x_1^2 + 3.277x_1x_2 + 4.470x_2^2$$

which gives the linear feedback

$$u_{\text{lin,per}}(x) = -1.636x_1 - 3.277x_2$$

Now (7) is satisfied on a sufficiently large area around zero. The set $\mathbf{A}$ is displayed in figure 3 (left) (white). The pre-images $\Omega = V^{-1}([0, 2])$ (grey) and $\Omega^\epsilon = V^{-1}([0, 1])$ with $\epsilon = 1$ (dark grey) are both inside the set $\mathbf{A}$.

Finally, we find a fourth order Lukes approximation for the Hamilton-Jacobi equation (14), using the same perturbation function as in the linear feedback case. We compute the formal storage function

$$\begin{aligned} V_{4\text{th,per}}(x) &= 0.818x_1^2 + 3.277x_1x_2 + 4.470x_2^2 \\ &+ 0.128x_1^2x_2^2 + 0.3113x_1x_2^3 + 0.025x_1^3x_2 \\ &+ 0.002x_1^4 + 0.4124x_2^4 \end{aligned}$$

which gives the third order feedback

$$\begin{aligned} u_{3\text{rd,per}}(x) &= -1.636x_1 - 3.277x_2 - 0.076x_1^2x_2 \\ &- 0.256x_1x_2^2 - 0.008x_1^3 - 0.311x_2^3 \end{aligned}$$

Figure 3 (right) shows a slightly improved set $\mathbf{A}$ (white). Note that the valid region $\Omega = V^{-1}([0, 4])$ (grey) is enlarged considerably. The set of valid initial conditions $\Omega^\epsilon = V^{-1}([0, 1])$ (dark grey) is approximatively the same as for the linear design. Note also that we have chosen $\epsilon = 3$, thereby allowing for valid disturbances of three times larger energy than in the linear case.

6. Conclusion

In this paper it is shown that state feedback problems involving the regional stabilization of the origin can successfully be recast as generalized formulations of nonlinear local state feedback H_∞ control problems. Given a formal solution V to a certain Hamilton-Jacobi inequality, the generalized problem is solved regionally provided V

Figure 3: Linear and third order control

is such that some connected component of the pre-image $V^{-1}(-\infty, c)$ for some $c \in \mathbb{R}$ is bounded and includes the origin. The plant is assumed to have the standard zero-detectability assumption. Sets of allowable initial conditions and disturbance classes are specified.

Performance is guaranteed in a range of operational conditions, in contrast to local H_∞ control. Numerical and symbolic computation methods which apply to local H_∞ theory can without problem be applied in a regional context.

Lukes approximation scheme is explained and implemented in the symbolic language MAPLE, and a formal, local storage function is computed. An example shows that the theory developed in this paper can be used to estimate the valid performance region (performance envelope) of linear as well as nonlinear state feedback controllers.

A Proof of theorem 3.2

By lemma 3.1 all $x(\cdot)$ are bounded inside Ω . Therefore, the L_2 gain (4) is satisfied.

We show now that all such $x(\cdot)$ generated by $w(\cdot) \in \mathbf{W}^\epsilon$ which are identically zero for all times $t > T$, $T \in \mathbb{R}$, approach the biggest closed loop invariant set M contained in the null set N . By state boundedness, and time invariance of the system, we can assume without loss of generality that $w(\cdot) = 0$ for all $t \in \mathbb{R}^+$. The saddle point property (6) implies that the C^1 solution V serves as a Lyapunov function for the closed loop dynamics. We have

$$\mathbf{H}_\gamma(u_{\min}, w) \leq \mathbf{H}_\gamma(u_{\min}, w_{\min}) = H_\gamma^{\min} \leq 0 \quad (17)$$

for all $w(\cdot) \in \mathbf{W}^\epsilon$. Choosing $w(\cdot) = 0$ then gives with (5)

$$\frac{d}{dt} V - \gamma^2 |0|^2 + |z|^2 \leq 0 \quad (18)$$

for all such $x(\cdot)$. Hence we have $\frac{d}{dt} V < 0$ for all $x(\cdot)$ evolving on Ω/N . Trajectories on N are satisfying $\frac{d}{dt} V = 0$ if and only if $|z|^2 = |Z(x, u_{\min}(x))|^2 = 0$, and $\frac{d}{dt} V < 0$ else.

Now observe that $V(x)$ by assumption is continuous and defined on a bounded set, hence $V(x)$ is bounded from below. Given some particular state $x(\cdot)$, the storage function $V(\cdot)$ is decreasing and bounded from below, hence approaches some minimal value, say $c_\Gamma \in \mathbb{R}$, as $t \rightarrow \infty$. By continuity we conclude that $V(x) = c_\Gamma$ on the positive limit set Γ^+ , and consequently $\frac{d}{dt} V = 0$ on Γ^+ . Rearranging (17) and (18) then

shows that

$$0 \leq |z|^2 \leq H_\gamma^{\min} \leq 0, \quad (19)$$

therefore we conclude that Γ^+ is a non-empty subset of the null set N . But Γ^+ is an invariant set, hence contained in the maximal invariant set M , and consequently any trajectory $x(\cdot)$ is approaching M as $t \rightarrow \infty$.

We show finally that zero-detectability implies that $x(\cdot)$ approaches the origin as $t \rightarrow \infty$. Clearly any trajectory evolving entirely on Γ^+ satisfies by (19) that $z(\cdot) = 0$, hence by zero-detectability the origin is approached. Finally, any trajectory with the same limit set $\Gamma^+ = \{0\}$ is by continuity of the closed loop dynamics forced to approach zero as $t \rightarrow \infty$.

References

- [BHW93] Joseph A. Ball, J. William Helton, and Michael L. Walker. H_∞ control for nonlinear systems with output feedback. *IEEE Transactions on Automatic Control*, 38(4):546–559, April 1993.
- [CMPP96] Marc Cromme, Jens Møller-Petersen, and Martin Pagh Petersen. Nonlinear H_∞ state feedback controllers: Computation of valid region. *Department of Mathematics, Technical University of Denmark*, MAT Report 1996-33, September 1996.
- [IA92a] Alberto Isidori and Alessandro Astolfi. Disturbance attenuation and H_∞ control via measurement feedback in nonlinear systems. *IEEE Transactions on Automatic Control*, 37(9):1283–1293, September 1992.
- [IA92b] Alberto Isidori and Alessandro Astolfi. Nonlinear H_∞ control via measurement feedback. *Journal of Mathematical Systems, Estimation, and Control*, 2(1):31–44, 1992.
- [IK95] Alberto Isidori and Wei Kang. H_∞ control via measurement feedback for general nonlinear systems. *IEEE Transactions on Automatic Control*, 40(3):466–472, March 1995.
- [Isi92] Alberto Isidori. Dissipation inequalities in nonlinear H_∞ control. In *Proceedings of the 31st Conference on Decision and Control; Tucson, Arizona*, pages 3265–3270, December 1992.
- [Luk69] D. L. Lukes. Optimal regulation of nonlinear dynamical systems. *SIAM Journal of Control*, 7:75–100, February 1969.
- [MP95] Jens Møller-Pedersen and Martin Pagh Petersen. Control of nonlinear plants: Volume I & II. Master's thesis, Mathematical Institute, Technical University of Denmark, August 1995. Available at <http://www.mat.dtu.dk/eksproj.html>.
- [SL61] Joseph La Salle and Solomon Lefschetz. *Stability by Liapunov's direct method*, chapter 2, pages 56–59. Academic Press, New York & London, 1961.
- [vdS92] A. J. van der Schaft. *Nonlinear State Space H_∞ Control Theory*, chapter 6, pages 153–190. Birkhäuser, 1992.
- [Wil72] Jan C. Willems. Dissipative dynamical systems part I: General theory. *Arch. Rational Mech. Anal.*, 45:321–351, 1972.