



Optoelectronic signal processing for chromatic dispersion mitigation in direct detection systems

Magalhães Ranzini, Stenio; Da Ros, Francesco; Bülow, Henning; Zibar, Darko

Published in:
Proceedings of 22nd International Conference on Transparent Optical Networks (ICTON)

Publication date:
2020

Document Version
Peer reviewed version

[Link back to DTU Orbit](#)

Citation (APA):
Magalhães Ranzini, S., Da Ros, F., Bülow, H., & Zibar, D. (2020). Optoelectronic signal processing for chromatic dispersion mitigation in direct detection systems. In *Proceedings of 22nd International Conference on Transparent Optical Networks (ICTON)* IEEE.

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

Optoelectronic signal processing for chromatic dispersion mitigation in direct detection systems

Stenio M. Ranzini^{1,2}, Francesco Da Ros¹, Henning Bülow², Darko Zibar¹

¹*DTU Fotonik, Technical University of Denmark, DK-2800 Kongens Lyngby, Denmark, smara@fotonik.dtu.dk*

²*Nokia Bell Labs, Lorenzstr. 10, 70435, Stuttgart, Germany*

ABSTRACT

An optical pre-processing structure is used to reduce the burden of digital equalizers and increase transmission reach for a direct detected system impaired by chromatic dispersion. The optical pre-processing consists of the optical signal being sliced into narrow frequency sub-band by an optical filter. Two distinct filters are numerically investigated: an arbitrary waveguide grating (AWG) filter and a series of cascaded Mach-Zehnder delay interferometers (MZDI). Each signal's spectral slice is detected by a photodetector and used as input for the digital equalizer. Two options are also considered for equalization: a feedforward neural network (NN) equalizer and a recurrent neural network with reservoir computing (RC). The results are analyzed in simulation in terms of signal-to-noise penalty at the KP4 forward error correction threshold. The penalty is calculated with respect to a back-to-back transmission without equalization. A 32 Gbd on-off transmission shows 0 dB penalty at ≈ 25 km transmission reach with optoelectronic processing with FNN and at ≈ 40 km with RC.

Keywords: Reservoir computing, signal equalization, chromatic dispersion mitigation, short-reach transmission, direct-detection.

1. INTRODUCTION

The ever increasing demand for data rates driven by the huge amount of new technologies that communicate with each other is challenging a sustainable growth for inter- and intra-datacenter communication. Transmission rate and reach need to be increased with a low-complexity solution. Direct detection systems are being considered given their low complexity, but losing the phase signal information makes chromatic dispersion compensation a major obstacle to increasing transmission reach. To overcome this challenge, solutions in the optical domain [1-2], digital/electronic domain [3-11] and joint optoelectronic approaches [12-20] are being considered. In our previous work, we showed that an optical pre-processing stage can be used to reduce the burden of the digital equalizer and, therefore, increasing the transmission reach at the expense of optical power loss [19, 20].

In this talk, we review our previous efforts on investigating methods to decrease the receiver complexity for a direct detection system, by sharing it between the optical and electrical domains. Additionally, we compare our previous results with an optoelectronic approach using a nonlinear digital equalizer based on reservoir computing (RC) [12-18; 21-22]. This machine learning method has the advantage of having the power of dynamic nonlinear systems with a simplified training stage. The results are numerically validated for a 32-GBd on-off keying transmission in a directly detected scenario considering an optical pre-amplifier.

ACKNOWLEDGMENTS

This project has received funding from the European Union's Horizon 2020 research and innovation programme under the Marie Skłodowska-Curie grant agreement No 766115, the European Research Council through the ERCCoG FRECOM project (grant agreement no. 771878) and by the YIP research grant (OPTIC-AI grant n. 29344) from VILLUM FONDEN.

REFERENCES

- [1] L. Grüner-Nielsen, S. N. Knudsen, B. Edvold, T. Veng, D. Magnussen, C. C. Larsen, and H. Damsgaard, Hans, "Dispersion compensating fibers", *Optical Fiber Technology*, 6(2), pp. 164–180, 2000.
- [2] N. M. Litchinitser, B. J. Eggleton, and D. B. Patterson, "Fiber Bragg gratings for dispersion compensation in transmission: theoretical model and design criteria for nearly ideal pulse recompression", *Journal of Lightwave Technology*, 15(8), pp. 1303–1313, 1997.
- [3] J. Jignesh, T. Eriksson, M. Chagnon, B. Corcoran, A. J. Lowery, F. Buchali, and H. Bülow, "Transmitter-side Volterra filtering for increased dispersion tolerance in 56 Gbaud PAM-4 systems", in *Proc. Optical Fiber Communication Conference (OFC)*, San Diego, CA, USA, March 2018, paper M2C.6.
- [4] M. Rubsamen, J. M. Gene, P. J. Winzer, and R.-J. Essiambre, "ISI mitigation capability of MLSE direct-detection receivers", *IEEE Photonics Technology Letters*, 20(8) pp. 656–658, 2008.
- [5] O. Agazzi, M. R. Hueda, H. S. Carrer, and E. D. Crivelli, "Maximum-likelihood sequence estimation in dispersive optical channels", *Journal of Lightwave Technology*, 23(2), pp. 749–763, 2005.
- [6] Q. Hu, M. Chagnon, K. Schuh, F. Buchali, and H. Bülow, "High Data Rate Tomlinson-Harashima precoding-Based Pam Transmission", in *Proc. European Conference on Optical Communication (ECOC)*, Dublin, Ireland, September 2019.
- [7] A. Mecozzi, C. Antonelli, M. Shtaif, "Kramers-Kronig coherent receiver", *Optica*, 3(11), pp. 1220–1227, 2006.
- [8] S. Gaiarin, X. Pang, O. Ozolins, R. T. Jones, E. P. da Silva, R. Schatz, U. Westergren, S. Popov, G. Jacobsen, and D. Zibar "High speed PAM-8 optical interconnects with digital equalization based on neural network". in *Proc. Asia Communications and Photonics Conference (ACP)*, Wuhan, China, November 2016, Paper AS1C-1.
- [9] M. Chagnon, B. Karanov, and L. Schmalen, "Experimental demonstration of a dispersion tolerant end-to-end deep learning-based im-dd transmission system", in *Proc. European Conference on Optical Communication (ECOC)*, Roma, Italy, September 2018. Paper Tu4F.6.

- [10] B. Karanov, D. Lavery, P. Bayvel, and L. Schmalen, "End-to-End Optimized Transmission over Dispersive Intensity-Modulated Channels Using Bidirectional Recurrent Neural Networks", *Optics Express*, **27**(14), pp. 19650–19663 (2019).
- [11] J. Estaran, R. Rios-Müller, R. M. A. Mestre, F. Jorge, H. Mardoyan, A. Konczykowska, J.-Y. Dupuy, and S. Bigo, "Artificial neural networks for linear and non-linear impairment mitigation in high-baudrate IM/DD systems", in *Proc. European Conference on Optical Communication (ECOC)*, Duresseldorf, Germany, September 2016.
- [12] P. Bienstman, J. Dambre, A. Katumba, M. Freiberger, F. Laporte, A. Lugnan, S. Sackesyn, and C. Ma, "Neuromorphic information processing using silicon photonics", in *Proc. SPIE 11081*, Active Photonic Platforms XI, 11081, September 2019.
- [13] A. Katumba, X. Yin; J. Dambre, and P. Bienstman, "A Neuromorphic Silicon Photonics Nonlinear Equalizer For Optical Communications With Intensity Modulation and Direct Detection", *Journal of Lightwave Technology*, **37**(10), pp. 2232–2239, May 2019.
- [14] S. Li, S. Ohlendorf, and S. Pachnicke, "100 km 56 GBd PAM-4 Transmission using Photonic Reservoir Computing", in *Proc. European Conference on Optical Communication (ECOC)*, September 2019, Paper Tu.2.B.
- [15] M. Sorokina, S. Sergeev, and S. Turitsyn, "Fiber echo state network analogue for high-bandwidth dual-quadrature signal processing", *Optics Express*, **27**(3) pp. 2387–2395, 2019.
- [16] A. Argyris, J. Bueno, and I. Fischer, "PAM-4 Transmission at 1550 nm Using Photonic Reservoir Computing Post-Processing", *IEEE Access*, **7** pp. 37017–37025, 2019.
- [17] A. Argyris, J. Bueno, and I. Fischer, "Photonic machine learning implementation for signal recovery in optical communications", *Scientific Reports*, **8**(1) pp. 8487, 2018.
- [18] D. Brunner, M.C. Soriano, G. Van der Sande, "Photonic Reservoir Computing", *Walter de Gruyter GmbH & Co KG*, 1st ed. , 2019
- [19] S. Ranzini, F. Da Ros, H. Bülow, and D. Zibar, "Tunable Optoelectronic Chromatic Dispersion Compensation Based on Machine Learning for Short-Reach Transmission", *Applied Sciences*, **9**(20) pp. 4332, 2019.
- [20] S. Ranzini, F. Da Ros and D. Zibar, "Joint low-complexity opto-electronic chromatic dispersion compensation for short-reach transmission", in *2019 IEEE Photonics Conference*, pp. 1-2, 2019.
- [21] J. Herbert, "The "echo state" approach to analysing and training recurrent neural networks". *Technical Report GMD Report 148*, German National Research Center for Information Technology, 2001.
- [22] W. Maass, T. Natschläger, and H. Markram, "Real-time computing without stable states: A new framework for neural computation based on perturbations". *Neural Computation*, **14**(11), pp. 2531–2560, 2002