Am angledetector based on magnetic sensing

Kaulberg, Thomas; Bogason, Gudmundur

Published in:

Proceedings of the IEEE International Symposium on Circuits and Systems

Link to article, DOI:

[10.1109/ISCAS.1994.409374](https://doi.org/10.1109/ISCAS.1994.409374)

Publication date:

1994

Document Version

Publisher's PDF, also known as Version of record

[Link back to DTU Orbit](#)

Citation (APA):

Kaulberg, T., & Bogason, G. (1994). Am angledetector based on magnetic sensing. In *Proceedings of the IEEE International Symposium on Circuits and Systems* (Vol. Volume 5, pp. 329-332). IEEE.
<https://doi.org/10.1109/ISCAS.1994.409374>

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

An Angledetector based on magnetic sensing

Thomas Kaulberg
Electronics Institute
Technical University of Denmark
DK-2800 LYNGBY
Denmark
(+45) 45 93 42 07
thomas@eiffel.ei.dth.dk

Gudmundur Bogason
Electronics Institute
Technical University of Denmark
DK-2800 LYNGBY
Denmark
(+45) 45 93 42 07
gudme@eiffel.ei.dth.dk

ABSTRACT

An angledetector with a digital output is described. The component is ment as an alternative to the traditional slide potentiometer used as volume control in many hearing aid applications. The component is based on the use of magnetic sensitive MOSFET's (MAGFET's) detecting the position of a tiny bar magnet placed above a silicon chip. Because of the galvanic separation between the anglesetting bar magnet and the electrical circuit, this component is insensitive to the rather hostile environment hearing aids are exposed to. The lifetime of the component is thereby increased significantly. The electrical circuit contains a switched current A/D - D/A conversion system for offset compensating the MAGFET's and for converting the MAGFET signal currents into a digital output proportional to the input angle. It is implemented using a commercially available $1.5\text{ }\mu\text{m}$ CMOS process.

INTRODUCTION

The volume control in hearing aid systems is often realized with a traditional slide potentiometer. Due to the hostile and humid environment in which it has to function and the galvanic contact between the metal pointer and the carbon slide, the lifetime of the component is rather limited. One way of avoiding the galvanic contact is letting magnetic sensitive transistors detect the position of a movable bar magnet as shown by Figure 1. An iron disk is placed beneath the chip to focus the magnetic field applied to the MAGFET's. The bar mag-

Figure 1. The Angledetecting system

net can make a 2π turn (there can be a physical stop to make only one turn possible) and two MAGFET's are used. One is placed at the angle $\theta = 0$ and one is placed at the angle $\theta = \pi/2$.

On the assumption that the differential output current of a MAGFET is proportional to the magnetic flux through it [3], a possible *Angle to Current*-transfer function is shown in Figure 2. $I_{D,M1}$ and $I_{D,M2}$ are the differential output currents of the two MAGFET's M1 and M2. The exact transfer function is a rather complex function of the dimensions of the bar magnet, the placement of the MAGFET's and the chosen materials.

From Figure 2 it is clear that any angle position unambiguously can be detected. This paper describes a

Figure 2. The MAGFET signal currents

solution where the angle position is to be represented by a 7 bit digital number proportional to the input angle. The two most significant bits (MSB) can be determined by simply reading the signs of the two MAGFET currents. This will divide the input angle into four equally sized intervals which can be represented by the two most significant bits. The third MSB can be provided by comparing the two currents numerically, $|I_{D,M1}| > |I_{D,M2}|$. The four least significant bits can be generated by A/D converting the numerical smallest current with the numerical largest current as a reference. This is in effect a division expressed by Eq. (1).

$$4 \text{ LSB} = f_{\text{dec}}(D_3 \dots D_0) = \frac{\min\{|I_{D,M1}|, |I_{D,M2}|\}}{\max\{|I_{D,M1}|, |I_{D,M2}|\}} \quad (1)$$

The f_{dec} function indicates that a decoding of the result is taking place. Simulations on the transfer function of the system indicate that an approximate linear *Angle to digital output*-transfer function indeed is achievable with a appropriate choice of dimensions and placement of the bar magnet and the MAGFET's and magnetic material. The simulations were based on the 'finite element' analysis method using the ANSYS program [1]. The dimensions of the entire chip is 2 mm $\times$ 2 mm and the dimensions of the bar magnet is 0.5 mm $\times$ 0.65 mm $\times$ 2 mm (HWL). The MAGFET will be exposed to a magnetic field in the range of ± 0.25 T.

THE MAGFET TRANSISTOR

A MAGFET is a MOSFET transistor with multiple drain terminals (typically 2 or 3 drains) [2] [3]. Due to the implementation (See Figure 3) of the MAGFET the differential drain current is dependent on the magnetic field applied to it.

The dimensions, the biasing and the topology of the MAGFET will influent important values as sensitivity to

Figure 3. MAGFET Layout

Figure 4. Cascade coupled MAGFET

magnetic field, linearity, noise, offset errors and the use of power and area. Measurements and the calculations can be seen in [4]. In this specific project the MAGFET has been implemented using four two-drain MAGFET's in cascade as shown in Figure 4. The dimensions of each MAGFET is $W/L = 62 \mu\text{m}/62 \mu\text{m}$ and there has been used a common centroid structure for the layout for lowering offset errors. The resulting MAGFET was found to have an approximate transfer function given by Eq. (2).

$$I_{D1} - I_{D2} = 0.32 \text{ T}^{-1} I_B B_{z,MAG}(\theta) + I_{OFF} \quad (2)$$

where $B_{z,MAG}(\theta)$ is the magnetic flux in the vertical direction at the given MAGFET.

The bias current was set to $I_B = 15 \mu\text{A}$ giving us a maximum differential signal current of $\pm 1.2 \mu\text{A}$. The cascade coupled MAGFET uses $120 \mu\text{A}$ and the offset current I_{OFF} is measured to be as high as 50 % of the maximum output current. This is mainly due to variations on the threshold voltage V_T . This large offset current cannot be accepted. An offset compensation is necessary to bring it to an acceptable level. For this purpose an 8 bit A/D - D/A system will be used.

Figure 5. The AD/DA system

THE A/D - D/A SYSTEM

The A/D - D/A system must be able to measure the offset error by an A/D conversion and make a permanent digital storage of the offset error. The stored offset error is then to be D/A converted and subtracted from the MAGFET current. The measuring and storing of the offset errors has to be done without any magnetic field applied to the MAGFET, i.e. before the bar magnet is placed on the top of the chip. The D/A conversion and the subtraction of the stored error from the MAGFET current must be carried out before any processing on the MAGFET currents can take place. It was decided to use the *successive approximation method* for A/D conversion because this conversion is based on a D/A converter (DAC). By using the same DAC in both the A/D and the D/A conversion unwanted nonlinearities in the D/A transfer function will cancel out. Also it is an efficient solution in terms of minimizing area.

For the purpose a serial DAC, which generates the MSB first and the LSB last, has been developed. The advantage of this solution, compared to a parallel DAC, is less use of area and no use of a *successive approximation register*. The D/A converter has been realized with the use of *switched current* technique and is described in detail in [4]. A block diagram of the entire system is shown in Figure 5.

The system is controlled by a finite state machine realized with a PLA. It works in two different modes. In **Mode 1** the two offset currents are measured (A/D converted) and stored digitally. In **Mode 2** the stored er-

ror signals are D/A converted and subtracted from the MAGFET currents and the position of the bar magnet is determined from the two offset compensated MAGFET currents. The sequences are shown schematically below.

Mode 1 : Storage of offset errors (No magnetic field applied)

1. 8 bit A/D conversion of $I_{M1,OFF}$
2. Storage of $I_{M1,OFF}$
3. 8 bit A/D conversion of $I_{M2,OFF}$
4. Storage of $I_{M2,OFF}$

Mode 2 : Position detection (Magnetic field applied)

1. 8 bit D/A conversion of $I_{M1,OFF}$
 $I_{M1,SIGNAL} = I_{M1} - I_{M1,OFF}$
2. 8 bit D/A conversion of $I_{M2,OFF}$
 $I_{M2,SIGNAL} = I_{M2} - I_{M2,OFF}$
3. $I_{M1,SIGNAL} > 0 ? ; I_{M2,SIGNAL} > 0 ?$
 $|I_{M1,SIGNAL}| > |I_{M2,SIGNAL}| ? \Rightarrow 3 \text{ MSB}$
4. 4 bit A/D conversion : $\frac{\min\{|I_{D,M1}|, |I_{D,M2}|\}}{\max\{|I_{D,M1}|, |I_{D,M2}|\}} \Rightarrow 4 \text{ LSB}$

A/D conversion : The A/D conversion of **Mode 1** utilizes all of the building blocks of Figure 5. The staircase generator is generating a sequence of MSB followed by 2.MSB etc. ending with LSB. When the output is MSB the output of the accumulator (MSB as well) is subtracted from the MAGFET current that is to be measured and the sign of the resulting current is shown on the output of the comparator. This sign signal is both shifted into the shift register and passed to the control